



New version 2019: novel 7 languages packaging & user manual;
Wider slots for 20700 & 21700 lithium batteries !

LUSH

Q4

Compatible With Lithium
IMR 3.6V/3.7V Batteries:

- | | |
|-------|-------|
| 10440 | 18500 |
| 14500 | 18650 |
| 16340 | 26500 |
| 17340 | 26650 |
| 18350 | 20700 |
| 18490 | 21700 |

AC input power ----- AC 100~240V 50/60Hz
 1*2.0A CC current ----- 2000mA±10%
 2*1.0A CC current ----- 1000mA±10%
 4*0.5A CC current ----- 500mA±10%
 Auto cut-off voltage ----- 4.20±0.05V
 CV cut-off current ----- < 10% max
 Standby current ----- <10.0mA
 Activation current (battery voltage<2.90V) ----- 10mA~50 mA
 Auto recharge voltage ----- 4.10±0.10V
 Operation Temperature ----- 0°C ~ 40°C
 Storage Temperature ----- -40°C ~ +70°C



CONVENIENT CHARGING FOR ANYWHERE YOU WANT AND ANYTIME YOU NEED.



DESCRIPTION

Efest LUSH Q4 LED Indicator Charger

- Fashion, modern and curve appearance
- Stylish & eye catching packaging
- High quality fire retardant material

FEATURES

- Three charging modes: 2.0A 1.0A 0.5A
- Auto-stop when fully charged & auto-recharge when voltage lower than 4.05V
- 4 kinds of protection over- discharging, over- voltage, short- circuit and reverse polarity protection
- The batteries at or over 0.6V can be activated by Q4 charger
- Battery slot monitors independently



CRAFTSMANSHIP

- Spring made by piano wire, it provides a smooth sliding action when installing and removing batteries.
- Steel cathode with low resistance and hard chromium plating processing to achieve a more precise charging voltage.
- 15,000+ times spring testing quality warranty



CERTIFICATIONS



Global Insurance technical support with
FCC,CE,RoHS certification.



PACKAGE

Newest 7 Languages Version
(EN/DE/FR/IT/ES/RU/JA)

WARNING



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Adapters category](#):

Click to view products by [EFEST manufacturer](#):

Other Similar products are found below :

[11904](#) [86-208-1-22](#) [13905](#) [86-207-1-22](#) [13904](#) [51957](#) [K-KJ55MCD40E](#) [HT8G616](#) [11903](#) [EE UNIVERSAL CHARGER 57658101401](#)
[EPA1205L](#) [PEAK POWER U813](#) [L3EFT-SLIMK4](#) [L3EFT-LUSHQ8](#) [L3EFT-LUSHBOX](#) [L3EFT-IMATER4](#) [L3EFT-IMATER2](#) [L3EFT-](#)
[SODA](#) [L3EFT-PROC4](#) [L3EFT-LUCV2](#) [L3EFT-ELITEV4](#) [L3EFT-LUCV4](#) [GDPT P2012-L2](#) [GDPT G600-168030](#) [BG21](#) [BM6018](#) [BM200-](#)
[05](#) [PCM-L03-D142](#) [PCM-L08-D142](#) [PCM-L07-D142](#) [PCM-L04-D142](#) [POLOLU MICROSD ADAPTER](#) [GROVE CAPE FOR](#)
[BEAGLEBONE](#) [GROVE BREAKOUT FOR LINKIT SMART 7688 DUO](#) [RBFN-EU-SEN-BMT-12](#) [9546](#) [9755](#) [9983](#) [51955](#) [51956](#) [51958](#)
[51959](#) [52479](#) [52480](#) [52481](#) [I2C HUB](#) [DUAL MAX14870 MOTOR DRIVER SHIELD](#) [6PRO122420](#) [AB-12.100/ST8VA](#) [B631-2B1](#)