



F&F Filipowski sp. j.
Konstantynowska 79/81 95-200 Pabianice
phone/fax: (+48 42) 215 23 83 / 227 09 71 POLAND
<http://www.fif.com.pl> e-mail: fif@fif.com.pl

„SOFT START”
for halogen lamps

MST-01

WARRANTY. The F&F products are covered by the 24 months warranty from date of purchase. Effective only with proof of purchase. Contact your dealer or directly from us. For more information on the procedures for filing complaints on: www.fif.com.pl/reklamacje



5 19 0 8 3 1 2 5 9 5 2 1 2 1





Do not dispose of this device in the trash along with other waste! According to the Law on Waste, electro coming from households free of charge and can give any amount to up to that end point of collection, as well as to store the occasion of the purchase of new equipment (in accordance with the principle of old-for-new, regardless of brand). Electro thrown in the trash or abandoned in nature, pose a threat to the environment and human health.

PURPOSE


MST is used to reduce the starting current of halogen lamps. This prevents over-connected lamps, in effect extending their service life.

FUNCTIONING

At the time of switching on the controller does not allow for immediate switch ON of light to full power. Initially the lamp system is powered by internal thermistor which limiting current circuit. After a time of 1sec. system switches to permanent contact, through which passes a full load of receivers. ATTENTION! No effect gradually illuminating of lamps.



WIRING DIAGRAM



ASSEMBLY

1. Take OFF the power.
2. Power cable 230V connect to joints 1-3.
3. System of powered lamps connect in parallel to joints 10-12.

TECHNICAL DATA

input Voltage	230V AC
output Voltage	230V AC
joint	1Z
current load	8A
rise time	1sec
power consumption of detection sensor	0,1W
working temperature	-25÷50°C
connection	screw terminals 2,5mm ²
dimensions	1 module (18mm)
fixing	on the rail TH-35

D140701

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Power Supplies - DIN Rail Mount](#) ***category:***

Click to view products by [F&F](#) ***manufacturer:***

Other Similar products are found below :

[DVPPS02](#) [PS-C24024](#) [ADNB040-24-1PM-C](#) [SS14011524](#) [PS-C12024](#) [PSC-2024](#) [PSC-4048](#) [PSC-48148](#) [PSS18/24/0.75](#) [PSD-A120W12](#)
[NDR-7524](#) [787-1200.](#) [AMED75-48SJZ](#) [9000-41034-0101000](#) [PSLR30N](#) [230/12VDC 2.5A](#) [50995](#) [50903](#) [EL50-D](#) [50996](#) [HDN-3024](#)
[ISED-120-24](#) [1335698](#) [POS DIN30W24](#) [EL50-B](#) [50905](#) [POS DIN30W15](#) [POS MDIN60W12](#) [HDN-3012](#) [POS DIN60W24](#)
[XCSD1030W012VAA](#) [POS DIN60W15](#) [50904](#) [KAA-8R-10S](#) [POS DIN100W15](#) [POS DIN30W12](#) [HDN-6012](#) [POS MDIN100W12](#) [POS](#)
[MDIN40W24](#) [POS DIN15W15](#) [AMED75-48SNZ](#) [AMED120-12S480NZ](#) [CSW241C](#) [POS DIN60W12](#) [POS DIN15W12](#) [POS DIN15W24](#)
[50912](#) [ESSENTIAL-PS/1AC/24DC/120W/EE](#) [POS DIN100W12](#) [POS MDIN100W24](#) [2467130000](#)