



# SABRE Board for Smart Devices Based on the i.MX 6 Series

The Smart Application Blueprint for Rapid Engineering (SABRE) board for smart devices was created to simplify product design by offering a feature-rich development platform that allows developers to work with the majority of the i.MX 6 series processor's primary features.

It provides you with a low-cost development platform which includes all primary features of the processors and serves as an example for how to layout complex, high-speed interfaces such as DDR. The SABRE board for smart devices includes complete hardware design files and board support packages (BSP) for Android™, Linux® and FreeRTOS™\*.

SABRE boards enable designers to quickly get started with i.MX 6 series processors. The MCIMX6QP-SDB enables development on i.MX 6QuadPlus and i.MX 6DualPlus processors. The MCIMX6Q-SDB enables development on i.MX 6Quad and i.MX 6Dual processors. The MCIMX6SX-SDB enables development on i.MX 6SoloX processors. There are a number of accessory boards that work with the SABRE-SDB to provide additional capabilities such as multi-touch display and Wi-Fi® connectivity.

## SABRE BOARD FOR SMART DEVICES SYSTEM CONTENTS

- ▶ i.MX 6QuadPlus, 6Quad or 6SoloX processor-based system
- ▶ Power supply
- ▶ Quick Start Guide
- ▶ Bootable SD card

## SOFTWARE AND TOOLS

The SABRE board comes with an SD card pre-installed with the Android operating system (MCIMX6QP-SDB & MCIMX6Q-SDB) or the Linux operating system (MCIMX6SX-SDB). Additional third-party and proprietary software is available. In addition to optimized BSPs, we also provide a large portfolio of optimized video, speech and audio codecs are available.

More information is available at [www.nxp.com/SABRESDB](http://www.nxp.com/SABRESDB).

Join fellow i.MX developers online at [www.imxcommunity.org](http://www.imxcommunity.org) — an active community of open source developers.

\* For ARM® Cortex®-M4 on i.MX 6SoloX applications processors



**FIGURE 1: MCIMX6QP-SDB**



**MCIMX6QP-SDB FEATURES**

<b>Processor</b>	<ul style="list-style-type: none"> <li>i.MX 6QuadPlus 1 GHz processor based on the ARM® Cortex®-A9 core</li> </ul>
<b>Development for</b>	<ul style="list-style-type: none"> <li>i.MX 6QuadPlus and i.MX 6DualPlus</li> </ul>
<b>Memory/Storage</b>	<ul style="list-style-type: none"> <li>1 GB DDR3 SDRAM up to 533 MHz (1066 MTPS) memory</li> <li>8 GB eMMC flash</li> </ul>
<b>Display</b>	<ul style="list-style-type: none"> <li>2 x LVDS connectors</li> <li>HDMI connector</li> <li>LCD expansion connector (parallel, 24-bit)</li> <li>MIPI DSI connector (two data lanes, 1 GHz each)</li> </ul>
<b>User Interface</b>	<ul style="list-style-type: none"> <li>Power, reset, volume buttons</li> </ul>
<b>Power Management</b>	<ul style="list-style-type: none"> <li>NXP MMPF0100F9</li> </ul>
<b>Audio</b>	<ul style="list-style-type: none"> <li>Audio codec</li> <li>Microphone and headphone jacks</li> </ul>
<b>Expansion Connector</b>	<ul style="list-style-type: none"> <li>Camera MIPI CSI port</li> <li>I<sup>2</sup>C, SSI, SPI signals</li> </ul>
<b>Connectivity</b>	<ul style="list-style-type: none"> <li>2 x Full-size SD/MMC card slots</li> <li>22-pin SATA connector</li> <li>10/100/1000 Ethernet port</li> <li>1 x USB 2.0 OTG port (micro USB)</li> <li>mPCIe® connector</li> </ul>
<b>Debug</b>	<ul style="list-style-type: none"> <li>JTAG connector (10-pin)</li> <li>1x Serial-to-USB connector (for JTAG)</li> </ul>
<b>OS Support</b>	<ul style="list-style-type: none"> <li>Linux® and Android™</li> <li>Others supported third party (QNX, Windows® Embedded)</li> </ul>
<b>Tools Support</b>	<ul style="list-style-type: none"> <li>Manufacturing Tool</li> <li>Processor Expert IOMUX tool</li> </ul>
<b>Additional Features</b>	<ul style="list-style-type: none"> <li>NXP MMA8451 three-axis accelerometer</li> <li>NXP MAG3110 three-axis magnetometer</li> <li>USB plug power supply</li> <li>NXP 3D magnetometer</li> </ul>

**FIGURE 2: MCIMX6Q-SDB**



**MCIMX6Q-SDB FEATURES**

<b>Processor</b>	<ul style="list-style-type: none"> <li>i.MX 6Quad 1 GHz processor based on the ARM® Cortex®-A9 core</li> </ul>
<b>Development for</b>	<ul style="list-style-type: none"> <li>i.MX 6Quad and i.MX 6Dual</li> </ul>
<b>Memory/Storage</b>	<ul style="list-style-type: none"> <li>1 GB DDR3 SDRAM up to 533 MHz (1066 MTPS) memory</li> <li>8 GB eMMC Flash</li> </ul>
<b>Display</b>	<ul style="list-style-type: none"> <li>2 x LVDS connectors</li> <li>HDMI connector</li> <li>LCD expansion connector (parallel, 24-bit)</li> <li>MIPI DSI connector (two data lanes, 1 GHz each)</li> </ul>
<b>User Interface</b>	<ul style="list-style-type: none"> <li>Power, reset, volume buttons</li> </ul>
<b>Power Management</b>	<ul style="list-style-type: none"> <li>NXP MMPF0100</li> </ul>
<b>Audio</b>	<ul style="list-style-type: none"> <li>Audio codec</li> <li>Microphone and headphone jacks</li> </ul>
<b>Expansion Connector</b>	<ul style="list-style-type: none"> <li>Camera MIPI CSI port</li> <li>I<sup>2</sup>C, SSI, SPI signals</li> </ul>
<b>Connectivity</b>	<ul style="list-style-type: none"> <li>2 x full-size SD/MMC card slots</li> <li>22-pin SATA connector</li> <li>10/100/1000 Ethernet port</li> <li>1 x USB 2.0 OTG port (micro USB)</li> <li>mPCIe® connector</li> </ul>
<b>Debug</b>	<ul style="list-style-type: none"> <li>JTAG connector (20-pin)</li> <li>1 x Serial-to-USB connector (for JTAG)</li> </ul>
<b>OS Support</b>	<ul style="list-style-type: none"> <li>Linux® and Android™</li> <li>Others supported third party (QNX, Windows® Embedded)</li> </ul>
<b>Tools Support</b>	<ul style="list-style-type: none"> <li>Manufacturing Tool</li> <li>Processor Expert IOMUX tool</li> </ul>
<b>Additional Features</b>	<ul style="list-style-type: none"> <li>NXP MMA8451 three-axis accelerometer</li> <li>NXP MAG3110 three-axis magnetometer</li> <li>USB plug power supply</li> <li>NXP 3D magnetometer</li> </ul>

**FIGURE 3: MCIMX6SX-SDB**



**MCIMX6SX-SDB FEATURES**

<b>Processor</b>	<ul style="list-style-type: none"> <li>i.MX 6SoloX 1 GHz processor based on the ARM® Cortex®-A9 core and 227 MHz Cortex-M4 core</li> </ul>
<b>Development for</b>	<ul style="list-style-type: none"> <li>i.MX 6SoloX</li> </ul>
<b>Memory/Storage</b>	<ul style="list-style-type: none"> <li>1 GB DDR3L SDRAM up to 400 MHz</li> <li>32 MB x 2 QSPI NOR flash</li> </ul>
<b>Display</b>	<ul style="list-style-type: none"> <li>LVDS connector</li> <li>LCD expansion connector (parallel, 24-bit)</li> </ul>
<b>User Interface</b>	<ul style="list-style-type: none"> <li>Buttons: Power (sw3), Reset (sw2), Function1, Function2</li> <li>Switch: power</li> </ul>
<b>Power Management</b>	<ul style="list-style-type: none"> <li>NXP MMPF0200</li> </ul>
<b>Audio</b>	<ul style="list-style-type: none"> <li>Audio codec</li> <li>Microphone and headphone jacks</li> <li>Board-mounted microphone</li> </ul>
<b>Expansion Connector</b>	<ul style="list-style-type: none"> <li>Parallel camera MIPI CSI port</li> <li>I<sup>2</sup>C and signals</li> </ul>
<b>Connectivity</b>	<ul style="list-style-type: none"> <li>Full-size SD/MMC card slots (3x)</li> <li>Two gigabit Ethernet connectors</li> <li>1 x USB 2.0 OTG port (micro USB)</li> <li>mPCIe® connector</li> <li>12-bit ADC connector</li> <li>2 x CAN (DB-9) using MC34901 CAN transceiver</li> </ul>
<b>Debug</b>	<ul style="list-style-type: none"> <li>JTAG connector (20-pin)</li> <li>1 x Serial-to-USB connector (for JTAG)</li> </ul>
<b>OS Support</b>	<ul style="list-style-type: none"> <li>Linux® and Android™, our proprietary MQX™ RTOS for ARM Cortex-M4</li> <li>Others supported via third party (QNX, Windows® Embedded)</li> </ul>
<b>Tools Support</b>	<ul style="list-style-type: none"> <li>Manufacturing tool</li> <li>Processor Expert IOMUX tool</li> </ul>
<b>Additional Features</b>	<ul style="list-style-type: none"> <li>MMA8451 three-axis accelerometer</li> <li>MAG3110 three-axis magnetometer</li> <li>Ambient light sensor</li> </ul>

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Development Boards & Kits - ARM category](#):*

*Click to view products by [NXP manufacturer](#):*

Other Similar products are found below :

[SAFETI-HSK-RM48](#) [PICOHOBBITFL](#) [CC-ACC-MMK-2443](#) [TWR-MC-FRDMKE02Z](#) [EVALSPEAR320CPU](#) [EVB-SCMIMX6SX](#)  
[MAX32600-KIT#](#) [TMDX570LS04HDK](#) [TXSD-SV70](#) [OM13080UL](#) [EVAL-ADUC7120QSPZ](#) [OM13082UL](#) [TXSD-SV71](#)  
[YGRPEACHNORMAL](#) [OM13076UL](#) [PICODWARFFL](#) [YR8A77450HA02BG](#) [3580](#) [32F3348DISCOVERY](#) [ATTINY1607](#) [CURIOSITY](#)  
[NANO](#) [PIC16F15376](#) [CURIOSITY NANO BOARD](#) [PIC18F47Q10](#) [CURIOSITY NANO](#) [VISIONSTK-6ULL V.2.0](#) [80-001428](#) [DEV-17717](#)  
[EAK00360](#) [YR0K77210B000BE](#) [RTK7EKA2L1S00001BE](#) [SLN-VIZN-IOT](#) [LV18F V6 DEVELOPMENT SYSTEM](#) [READY FOR AVR](#)  
[BOARD](#) [READY FOR PIC BOARD](#) [READY FOR PIC \(DIP28\)](#) [AVRPLC16 V6 PLC SYSTEM](#) [MIKROLAB FOR AVR XL](#) [MIKROLAB](#)  
[FOR PIC L](#) [MINI-AT BOARD - 5V](#) [MINI-M4 FOR STELLARIS](#) [MOD-09.Z](#) [BUGGY + CLICKER 2 FOR PIC32MX + BLUETOOT](#) [1410](#)  
[LETS MAKE PROJECT PROGRAM. RELAY PIC](#) [LETS MAKE - VOICE CONTROLLED LIGHTS](#) [LPC-H2294](#) [DSPIC-READY2 BOARD](#)  
[DSPIC-READY3 BOARD](#) [MIKROBOARD FOR ARM 64-PIN](#) [MIKROLAB FOR AVR](#) [MIKROLAB FOR AVR L](#) [MIKROLAB FOR](#)  
[DSPIC](#)