

## 200A Mini Clamp Meters + Non-contact Voltage Detector

### Clamp meters with built-in AC NCV Voltage detector + flashlight

200A mini clamp meters increase use safety by including a built-in voltage detector in the jaw tip. The user can now detect the presence of live voltages before using the meter.

#### Common Features:

- 0.7" (18mm) jaw opening; 300MCM cable size
- Built-in AC non-contact Voltage (NCV) detector (120/240VAC, 50/60Hz)
- LCD backlit display
- Built-in white LED flashlight
- Auto Power Off
- Complete with two AAA batteries and soft case

#### MA120 Additional Features:

- Measures AC/DC Current and Frequency
- Data Hold and Zero function

#### MA150 Additional Features:

- Measures AC Current, AC/DC Voltage, and Resistance
- Diode and Continuity test
- Max hold function



Bright LED Flashlight



Built-in non-contact voltage (NCV) detector via clamp tip

Specifications	MA120	MA150
AC Current	200A	200A
Max Resolution	100mA	100mA
Accuracy	±3.0%	±2.5%
DC Current	200A	—
Max Resolution	0.1A	—
Accuracy	±3%	—
AC Voltage	Non-contact	Non-contact/600V
Max Resolution	—	0.1mV
DC Voltage	—	600V
Max Resolution	—	0.1mV
Resistance	—	20MΩ
Max Resolution	—	0.1Ω
Accuracy	—	±3.0%
Frequency	1kHz	—
Max Resolution	0.01Hz	—
Dimensions	7x2.5x1.3" (178x65x32mm)	7x2.5x1.3" (178x65x32mm)
Weight	6 oz (170g)	6 oz (170g)

#### Ordering Information:

- MA120 .....200A AC/DC Mini Clamp Meter with Non-Contact Voltage Detector  
 MA120-NIST .....MA120 with Certification of Calibration Traceable to NIST  
 MA150 .....200A AC Mini Clamp Meter with Non-Contact Voltage Detector  
 MA150-NIST .....MA150 with Certification of Calibration Traceable to NIST



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Teledyne FLIR / Extech](#) manufacturer:*

Other Similar products are found below :

[I800](#) [MT-8006B](#) [3PK-NT023N](#) [MT-7057N](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM162](#) [BM197](#) [KEW2210R](#)  
[FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I310S](#) [TESTO 770-2 0590 7702](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [ACDC-](#)  
[100](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#) [FLUKE-1630-2FC](#) [CM42](#) [FLUKE-376 FC](#) [A193 \(800 MM\)](#) [F201](#) [F205](#) [F65](#) [DIGIFLEX](#)  
[4000A 350MM](#) [DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#) [MN93A](#) [FLUKE I6000SFLEX-24](#) [KEW2010](#) [P1670](#) [FLK-A3004FC](#)  
[AMP-330-EUR](#) [APPA SFLEX-18D](#) [UT200A](#) [UT201](#) [UT205](#) [UT205A](#) [UT206](#) [UT206A](#) [UT210A](#) [UT210B](#)