



New version 2019, Efest SLIM K1 charger comes with novel 7 languages packaging & user manual ! Lightweight and practical, fashion and convenient !



SLIM

K1



Compatible With Lithium
IMR 3.6V/3.7V Batteries:

- 10440
- 18500
- 14500
- 18650
- 16340
- 26500
- 17340
- 26650
- 18350
- 20700
- 18490
- 21700

AC input Power ----- AC 100~240V 50/60Hz
 DC input power ----- DC 5V 1A
 DC output Power ----- DC 5V 1A
 1*1A CC current ----- 1000mA±10%
 Auto cut-off voltage ----- 4.20±0.05V
 CV cut-off current ----- <100mA
 Standby current ----- <20mA
 Activation current ----- 50mA~100 mA
 Auto recharge voltage ----- 4.10±0.10V
 Operation Temperature ----- 0°C ~ 40°C
 Storage Temperature ----- -40°C ~ +70°C



CONVENIENT CHARGING FOR ANYWHERE YOU WANT AND ANYTIME YOU NEED.

DESCRIPTION

Efest SLIM K1 USB Charger

- Stylish & eye catching design
- Incredibly lightweight and conveniently portable
- Safe and handy 5V 1A USB charger



FEATURES

- Fast charging mode: 1.0A
- Reverse polarity protection
- Activation function
- Auto-detect charging function
- Over-charging protection
- Short circuit protection



CRAFTSMANSHIP

- Spring made by piano wire, it provides a smooth sliding action when installing and removing batteries
- Steel cathode with low resistance and hard chromium plating processing to achieve a more precise charging voltage
- 15,000+ times spring testing quality warranty



CERTIFICATIONS



Global Insurance technical support with FCC,CE,RoHS certification.

PACKAGE

Newest 7 Languages Version
(EN/DE/FR/IT/ES/RU/JA)

WARNING



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Adapters category](#):

Click to view products by [EFEST manufacturer](#):

Other Similar products are found below :

[11904](#) [86-208-1-22](#) [13905](#) [86-207-1-22](#) [13904](#) [51957](#) [K-KJ55MCD40E](#) [HT8G616](#) [11903](#) [EE UNIVERSAL CHARGER 57658101401](#)
[EPA1205L](#) [PEAK POWER U813](#) [L3EFT-SLIMK4](#) [L3EFT-LUSHQ8](#) [L3EFT-LUSHBOX](#) [L3EFT-IMATER4](#) [L3EFT-IMATER2](#) [L3EFT-](#)
[SODA](#) [L3EFT-PROC4](#) [L3EFT-LUCV2](#) [L3EFT-ELITEV4](#) [L3EFT-LUCV4](#) [GDPT P2012-L2](#) [GDPT G600-168030](#) [BG21](#) [BM6018](#) [BM200-](#)
[05](#) [PCM-L03-D142](#) [PCM-L08-D142](#) [PCM-L07-D142](#) [PCM-L04-D142](#) [POLOLU MICROSD ADAPTER](#) [GROVE CAPE FOR](#)
[BEAGLEBONE](#) [GROVE BREAKOUT FOR LINKIT SMART 7688 DUO](#) [RBFN-EU-SEN-BMT-12](#) [9546](#) [9755](#) [9983](#) [51955](#) [51956](#) [51958](#)
[51959](#) [52479](#) [52480](#) [52481](#) [I2C HUB](#) [DUAL MAX14870 MOTOR DRIVER SHIELD](#) [6PRO122420](#) [AB-12.100/ST8VA](#) [B631-2B1](#)