



Figure similar

SIMATIC S7-300, Analog input SM 331, isolated, 8 AI, Resolution 9/12/14 bits, U/I/thermocouple/resistor, alarm, diagnostics, 1x 20-pole Removing/inserting with active backplane bus

Supply voltage	
Load voltage L+	
• Rated value (DC)	24 V
• Reverse polarity protection	Yes
Input current	
from load voltage L+ (without load), max.	30 mA
from backplane bus 5 V DC, max.	50 mA
Power loss	
Power loss, typ.	1 W
Analog inputs	
Number of analog inputs	8
• For resistance measurement	4
permissible input voltage for voltage input (destruction limit), max.	20 V; continuous; 75 V for max. 1 s (mark to space ratio 1:20)
permissible input current for current input (destruction limit), max.	40 mA
Constant measurement current for resistance-type transmitter, typ.	1.67 mA
Input ranges	
• Voltage	Yes
• Current	Yes
• Thermocouple	Yes
• Resistance thermometer	Yes
• Resistance	Yes
Input ranges (rated values), voltages	
• 0 to +10 V	No
• 1 V to 5 V	Yes
— Input resistance (1 V to 5 V)	100 kΩ
• 1 V to 10 V	No
• -1 V to +1 V	Yes
— Input resistance (-1 V to +1 V)	10 MΩ
• -10 V to +10 V	Yes
— Input resistance (-10 V to +10 V)	100 kΩ
• -2.5 V to +2.5 V	Yes
— Input resistance (-2.5 V to +2.5 V)	100 kΩ
• -250 mV to +250 mV	Yes
— Input resistance (-250 mV to +250 mV)	10 MΩ
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	100 kΩ
• -50 mV to +50 mV	No

<ul style="list-style-type: none"> <li>● -500 mV to +500 mV <ul style="list-style-type: none"> <li>— Input resistance (-500 mV to +500 mV)</li> </ul> </li> <li>● -80 mV to +80 mV <ul style="list-style-type: none"> <li>— Input resistance (-80 mV to +80 mV)</li> </ul> </li> </ul>	<p>Yes</p> <p>10 MΩ</p> <p>Yes</p> <p>10 MΩ</p>
<b>Input ranges (rated values), currents</b>	
<ul style="list-style-type: none"> <li>● 0 to 20 mA <ul style="list-style-type: none"> <li>— Input resistance (0 to 20 mA)</li> </ul> </li> <li>● -10 mA to +10 mA <ul style="list-style-type: none"> <li>— Input resistance (-10 mA to +10 mA)</li> </ul> </li> <li>● -20 mA to +20 mA <ul style="list-style-type: none"> <li>— Input resistance (-20 mA to +20 mA)</li> </ul> </li> <li>● -3.2 mA to +3.2 mA <ul style="list-style-type: none"> <li>— Input resistance (-3.2 mA to +3.2 mA)</li> </ul> </li> <li>● 4 mA to 20 mA <ul style="list-style-type: none"> <li>— Input resistance (4 mA to 20 mA)</li> </ul> </li> </ul>	<p>Yes</p> <p>25 Ω</p>
<b>Input ranges (rated values), thermocouples</b>	
<ul style="list-style-type: none"> <li>● Type B</li> <li>● Type C</li> <li>● Type E <ul style="list-style-type: none"> <li>— Input resistance (Type E)</li> </ul> </li> <li>● Type J <ul style="list-style-type: none"> <li>— Input resistance (type J)</li> </ul> </li> <li>● Type K <ul style="list-style-type: none"> <li>— Input resistance (Type K)</li> </ul> </li> <li>● Type L <ul style="list-style-type: none"> <li>— Input resistance (Type L)</li> </ul> </li> <li>● Type N <ul style="list-style-type: none"> <li>— Input resistance (Type N)</li> </ul> </li> <li>● Type R</li> <li>● Type S</li> <li>● Type T</li> <li>● Type U</li> <li>● Type TXK/TXK(L) to GOST</li> </ul>	<p>No</p> <p>No</p> <p>Yes</p> <p>10 MΩ</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p>
<b>Input ranges (rated values), resistance thermometer</b>	
<ul style="list-style-type: none"> <li>● Cu 10</li> <li>● Ni 100 <ul style="list-style-type: none"> <li>— Input resistance (Ni 100)</li> </ul> </li> <li>● Ni 1000</li> <li>● LG-Ni 1000</li> <li>● Ni 120</li> <li>● Ni 200</li> <li>● Ni 500</li> <li>● Pt 100 <ul style="list-style-type: none"> <li>— Input resistance (Pt 100)</li> </ul> </li> <li>● Pt 1000</li> <li>● Pt 200</li> <li>● Pt 500</li> </ul>	<p>No</p> <p>Yes; Standard</p> <p>10 MΩ</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>Yes; Standard</p> <p>10 MΩ</p> <p>No</p> <p>No</p> <p>No</p>
<b>Input ranges (rated values), resistors</b>	
<ul style="list-style-type: none"> <li>● 0 to 150 ohms <ul style="list-style-type: none"> <li>— Input resistance (0 to 150 ohms)</li> </ul> </li> <li>● 0 to 300 ohms <ul style="list-style-type: none"> <li>— Input resistance (0 to 300 ohms)</li> </ul> </li> <li>● 0 to 600 ohms <ul style="list-style-type: none"> <li>— Input resistance (0 to 600 ohms)</li> </ul> </li> <li>● 0 to 6000 ohms</li> </ul>	<p>Yes</p> <p>10 MΩ</p> <p>Yes</p> <p>10 MΩ</p> <p>Yes</p> <p>10 MΩ</p> <p>No</p>
<b>Thermocouple (TC)</b>	
<ul style="list-style-type: none"> <li>— Temperature compensation <ul style="list-style-type: none"> <li>— parameterizable</li> <li>— internal temperature compensation</li> <li>— external temperature compensation with compensations socket</li> </ul> </li> </ul>	<p>Yes</p> <p>Yes</p> <p>Yes</p>

— for definable comparison point temperature	Yes
<b>Characteristic linearization</b>	
• parameterizable	Yes
— for thermocouples	Type E, J, K, L, N
— for resistance thermometer	Pt100 (standard, climatic range), Ni100 (standard, climatic range)
<b>Cable length</b>	
• shielded, max.	200 m; 50 m at 80 mV and thermocouples
<b>Analog value generation for the inputs</b>	
<b>Integration and conversion time/resolution per channel</b>	
• Resolution with overrange (bit including sign), max.	15 bit; Unipolar: 9/12/12/14 bit; bipolar: 9 bit + sign/12 bit + sign/12 bit + sign/14 bit + sign
• Integration time, parameterizable	Yes; 2,5 / 16,67 / 20 / 100 ms
• Basic conversion time (ms)	3 / 17 / 22 / 102 ms
• Interference voltage suppression for interference frequency f1 in Hz	400 / 60 / 50 / 10 Hz
<b>Encoder</b>	
<b>Connection of signal encoders</b>	
• for voltage measurement	Yes
• for current measurement as 2-wire transducer	Yes
• for current measurement as 4-wire transducer	Yes
• for resistance measurement with two-wire connection	Yes
• for resistance measurement with three-wire connection	Yes
• for resistance measurement with four-wire connection	Yes
<b>Errors/accuracies</b>	
<b>Operational error limit in overall temperature range</b>	
• Voltage, relative to input range, (+/-)	1 %; ±1% (80 mV); ±0.6% (250 mV to 1 000 mV); ±0.8% (2.5 V to 10 V)
• Current, relative to input range, (+/-)	0.7 %; From 3.2 to 20 mA
• Resistance, relative to input range, (+/-)	0.7 %; 150, 300, 600 Ohm
• Resistance thermometer, relative to input range, (+/-)	0.7 %; ±0.7 % (Pt100/ Ni100); ±0.8 % (Pt100 climate)
• Thermocouple, relative to input range, (+/-)	1.1 %; Type E, J, K, L, N
<b>Basic error limit (operational limit at 25 °C)</b>	
• Voltage, relative to input range, (+/-)	0.6 %; ±0.4 % (250 mV to 1 000 mV); ±0.6 % (2.5 mV to 10 mV); ±0.7 % (80 mV)
• Current, relative to input range, (+/-)	0.5 %; 3.2 to 20 mA
• Resistance, relative to input range, (+/-)	0.5 %; 150, 300, 600 Ohm
• Resistance thermometer, relative to input range, (+/-)	0.6 %; ±0.5% (Pt100/ Ni100), ±0.6% (Pt100 climate)
• Thermocouple, relative to input range, (+/-)	0.7 %; Type E, N, J, K, L
<b>Interrupts/diagnostics/status information</b>	
Diagnostics function	Yes; Parameterizable
<b>Alarms</b>	
• Diagnostic alarm	Yes; Parameterizable, channels 0 and 2
• Limit value alarm	Yes; Parameterizable
<b>Diagnoses</b>	
• Diagnostic information readable	Yes
<b>Diagnostics indication LED</b>	
• Group error SF (red)	Yes
<b>Potential separation</b>	
<b>Potential separation analog inputs</b>	
• between the channels	No
• between the channels and backplane bus	Yes
• between the channels and the power supply of the electronics	Yes
<b>Isolation</b>	
Isolation tested with	500 V DC
<b>connection method</b>	
required front connector	20-pin
<b>Dimensions</b>	
Width	40 mm
Height	125 mm
Depth	117 mm
<b>Weights</b>	

---

Weight, approx.

250 g

**last modified:**

8/16/2023 

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Interface Modules](#) category:*

*Click to view products by [Siemens](#) manufacturer:*

Other Similar products are found below :

[FAB118](#) [ATX6022/14GP7](#) [ATX6022/8](#) [9441560000](#) [73-546-001](#) [PCE-DP10-00A1E](#) [SNAP-PAC-SB2](#) [ADAM-4510S-F](#) [USB-CARD-READER](#) [USB-RS485](#) [USB-SATA](#) [TD501D232H](#) [RSM232D](#) [TD502D232H](#) [RS232 TO RS485](#) [TD302D232H](#) [TD501D232H](#) [RSM232](#) [RSM232D](#) [TD301D232H](#) [TD302D232H](#) [TD502D232H](#) [20270](#) [20294](#) [30255](#) [50260](#) [20295](#) [50261](#) [EUR0001H](#) [ZHB2301G](#) [4000-68512-0940003](#) [6ES73317KF020AB0](#) [6ES71556AA010BN0](#) [6ES71936AR000AA0](#) [BB-USPTL4](#) [1020882](#) [1021056](#) [1021058](#) [1021080](#) [73-544-002](#) [4000-68000-0010000](#) [UC-357](#) [485LDRC9](#) [485OPDRI](#) [U442-DOCK1](#) [UH104](#) [US-257](#) [422LP9R](#) [422PP9R](#) [422PP9TB](#)