TOSHIBA CMOS Digital Integrated Circuit Silicon Monolithic

# TC74VHC540F, TC74VHC540FK TC74VHC541F, TC74VHC541FK

Octal Bus Buffer TC74VHC540F/FK TC74VHC541F/FK

Inverted, 3-State Outputs Non-Inverted, 3-State Outputs

The TC74VHC540/TC74VHC541 are advanced high speed CMOS OCTAL BUS BUFFERs fabricated with silicon gate  $\rm C^2MOS$  technology.

They achieve the high speed operation similar to equivalent Bipolar Schottky TTL while maintaining the CMOS low power dissipation.

The TC74VHC540 is an inverting type, and the TC74VHC541 is a non-inverting type.

When either  $\overline{G}1\,$  or  $\,\overline{G}2\,$  are high, the terminal outputs are in the high-impedance state.z

An input protection circuit ensures that 0 to 5.5 V can be applied to the input pins without regard to the supply voltage. This device can be used to interface 5 V to 3 V systems and two supply systems such as battery back up. This circuit prevents device destruction due to mismatched supply and input voltages.

#### Features

- High speed: tpd = 3.7 ns (typ.) at VCC = 5 V
- Low power dissipation: ICC = 4 μA (max) at Ta = 25°C
- High noise immunity: VNIH = VNIL = 28% VCC (min)
- Power down protection is provided on all inputs.
- Balanced propagation delays:  $t_{pLH} \simeq t_{pHL}$
- Wide operating voltage range: VCC (opr) = 2 V to 5.5 V
- Low noise: VOLP = 1.0 V (max)
- Pin and function compatible with 74ALS540/541

TC74VHC540F, TC74VHC541F
RUURUURU
10/401103401 K, 10/401103411 K
CULURIN
VSSOP20-P-0030-0.50
Weight SOP20-P-300-1.27A : 0.22 g (typ.)

: 0.03 g (typ.)

VSSOP20-P-0030-0.50

# TOSHIBA

# **Pin Assignment**





# **IEC Logic Symbol**



# **Truth Table**

	Inputs	Out	puts	
G1	Ğ2	An	Yn	$\overline{Y}_n$
Н	Х	Х	Z	Z
Х	Н	Х	Z	Z
L	L	Н	Н	L
L	L	L	L	Н

X: Don't care

Z: High impedance

Yn: TC74VHC541

Yn: TC74VHC540

	TC74	VHC5	41		
$\overline{G1} \xrightarrow{(1)}$ $\overline{G2} \xrightarrow{(19)}$	&	EN			
A1 (2) A2 (3) A3 (4) A4 (5) A5 (6) A6 (7) A7 (8) A8 (9)			▽	(18) (17) (16) (15) (14) (13) (12) (11)	Y1 Y2 Y3 Y4 Y5 Y6 Y7 Y8

# **Absolute Maximum Ratings (Note)**

Characteristics	Symbol	Rating	Unit
Supply voltage range	Vcc	-0.5 to 7.0	V
DC input voltage	VIN	-0.5 to 7.0	V
DC output voltage	Vout	-0.5 to Vcc + 0.5	V
Input diode current	liк	-20	mA
Output diode current	lok	±20	mA
DC output current	IOUT	±25	mA
DC V <sub>CC</sub> /ground current	Icc	±75	mA
Power dissipation	PD	180	mW
Storage temperature	T <sub>stg</sub>	-65 to 150	°C

Note: Exceeding any of the absolute maximum ratings, even briefly, lead to deterioration in IC performance or even destruction.

Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings and the operating ranges.

Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook ("Handling Precautions"/"Derating Concept and Methods") and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

# **Operating Ranges (Note)**

Characteristics	Symbol	Rating	Unit
Supply voltage	Vcc	2.0 to 5.5	V
Input voltage	VIN	0 to 5.5	V
Output voltage	Vout	0 to Vcc	V
Operating temperature	Topr	-40 to 85	°C
Input rise and fall time	dt/dv	0 to 100 (V <sub>CC</sub> = 3.3 ± 0.3 V) 0 to 20 (V <sub>CC</sub> = 5 ± 0.5 V)	ns/V

Note: The operating ranges must be maintained to ensure the normal operation of the device.. Unused inputs must be tied to either V<sub>CC</sub> or GND.

# **Electrical Characteristics**

#### **DC Characteristics**

Characteristics	Symbol	Test Condition		Ta = 25°C			Ta = −40 to 85°C		Unit	
Characteriolice				V <sub>CC</sub> (V)	Min	Тур.	Max	Min	Max	OIII
High-level input		_		2.0	1.50		_	1.50	_	
voltage	ViH			3.0 to 5.5	Vcc × 0.7	—	—	Vcc × 0.7	—	V
Low-level input				2.0	_	-	0.50	-	0.50	
voltage	VIL	—		3.0 to 5.5	—		V <sub>CC</sub> × 0.3		V <sub>CC</sub> × 0.3	V
				2.0	1.9	2.0	-	1.9	_	
	Vон	VIN = VIH or VIL	I <sub>OH</sub> = −50 µA	3.0	2.9	3.0		2.9	—	V
High-level output				4.5	4.4	4.5	_	4.4	—	
renage			I <sub>OH</sub> = −4 mA	3.0	2.58	_	_	2.48	—	
			I <sub>OH</sub> = −8 mA	4.5	3.94	—		3.80	—	
	Vol	VIN = VIH or VIL		2.0	_	0.0	0.1	_	0.1	
			l <sub>OL</sub> = 50 μA	3.0	—	0.0	0.1	—	0.1	
Low-level output				4.5	—	0.0	0.1		0.1	V
vollage			$I_{OL} = 4 \text{ mA}$	3.0	_	_	0.36	-	0.44	
			I <sub>OL</sub> = 8 mA	4.5	—	—	0.36	—	0.44	
3-state output off- state current	I <sub>OZ</sub>	V <sub>IN</sub> = V <sub>IH</sub> or V <sub>IL</sub> V <sub>OUT</sub> = V <sub>CC</sub> or GND		5.5	_	_	±0.25	_	±2.50	μA
Input leakage current	lın	VIN = 5.5 V or GND		0 to 5.5	_	_	±0.1	_	±1.0	μA
Quiescent supply current	Icc	VIN = VCC or	GND	5.5	—	_	4.0	—	40.0	μA

AC Characteristics (input: tr = tf = 3 ns)

Characteristics	Symbol	Test Condition		Ta = 25°C			Ta = −40 to 85°C		Unit	
			V <sub>CC</sub> (V)	C <sub>L</sub> (pF)	Min	Тур.	Max	Min	Max	Onit
				15	_	4.8	7.0	1.0	8.5	
Propagation delay	tpLH		$3.3 \pm 0.3$	50	_	7.3	10.5	1.0	12.0	
(TC74VHC540)	tpHL	_	50.05	15	_	3.7	5.0	1.0	6.0	ns
			$5.0 \pm 0.5$	50	_	5.2	7.0	1.0	8.0	
			22.02	15	—	5.0	7.0	1.0	8.5	
Propagation delay	tpLH		$3.3 \pm 0.3$	50	_	7.5	10.5	1.0	12.0	<b>n</b> 0
(TC74VHC541)	t <sub>pHL</sub>	_	5.0 ± 0.5	15	_	3.5	5.0	1.0	6.0	
. ,				50	_	5.0	7.0	1.0	8.0	
	tpZL tpZH	R <sub>L</sub> = 1 kΩ	3.3 ± 0.3	15	—	6.8	10.5	1.0	12.5	- ns
3-state output enable				50	_	9.3	14.0	1.0	16.0	
time			5.0 ± 0.5	15	_	4.7	7.2	1.0	8.5	
				50	_	6.2	9.2	1.0	10.5	
3-state output disable	tpLZ tpHZ	RL = 1 kΩ	$3.3 \pm 0.3$	50	_	11.2	15.4	1.0	17.5	
time			5.0 ± 0.5	50	_	6.0	8.8	1.0	10.0	ns
	tosHL	(Note 1)	3.3 ± 0.3	50	_	_	1.5	_	1.5	
Output to output skew	tosLH	(Note T)	5.0 ± 0.5	50	_	_	1.0	_	1.0	ns
Input capacitance	CIN		_		_	4	10	_	10	pF
Output capacitance	COUT	_			—	6	—	—	—	pF
Power dissipation	Coo	TC74VHC540		_	17	_	_	_	۳E	
capacitance (Note 2)	CPD	TC74VHC541			_	18	_	_	_	рг

Note 1: Parameter guaranteed by design.

tosLH = |tpLHm - tpLHn|, tosHL = |tpHLm - tpHLn|

Note 2: CPD is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.

Average operating current can be obtained by the equation:

 $ICC (opr) = CPD \cdot VCC \cdot fIN + ICC/8 (per bit)$ 

### Noise Characteristics (input: tr = tf = 3 ns)

Characteristics	Cumbol	Test Condition	Ta =	l loit		
Characteristics	Symbol		V <sub>CC</sub> (V)	Тур.	Limit	Unit
Quiet output maximum dynamic $V_{OL}$	VOLP	C <sub>L</sub> = 50 pF	5.0	0.7	1.0	V
Quiet output minimum dynamic $V_{OL}$	VOLV	C <sub>L</sub> = 50 pF	5.0	-0.7	-1.0	V
Minimum high level dynamic input voltage	Vihd	CL = 50 pF	5.0	-	3.5	V
Maximum low level dynamic input voltage	VILD	CL = 50 pF	5.0	_	1.5	V



# Input Equivalent Circuit





# **Package Dimensions**

SOP20-P-300-1.27A

Unit: mm



Weight: 0.22 g (typ.)



# **Package Dimensions**

VSSOP20-P-0030-0.50

Unit: mm





Weight: 0.03 g (typ.)

# **RESTRICTIONS ON PRODUCT USE**

Toshiba Corporation and its subsidiaries and affiliates are collectively referred to as "TOSHIBA". Hardware, software and systems described in this document are collectively referred to as "Product".

- TOSHIBA reserves the right to make changes to the information in this document and related Product without notice.
- This document and any information herein may not be reproduced without prior written permission from TOSHIBA. Even with TOSHIBA's written permission, reproduction is permissible only if reproduction is without alteration/omission.
- Though TOSHIBA works continually to improve Product's quality and reliability, Product can malfunction or fail. Customers are responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of Product could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Before customers use the Product, create designs including the Product, or incorporate the Product into their own applications, customers must also refer to and comply with (a) the latest versions of all relevant TOSHIBA information, including without limitation, this document, the specifications, the data sheets and application notes for Product and the precautions and conditions set forth in the "TOSHIBA Semiconductor Reliability Handbook" and (b) the instructions for the application with which the Product will be used with or for. Customers are solely responsible for all aspects of their own product design or applications, including but not limited to (a) determining the appropriateness of the use of this Product in such design or applications; (b) evaluating and determining the applicability of any information contained in this document, or in charts, diagrams, programs, algorithms, sample application circuits, or any other referenced documents; and (c) validating all operating parameters for such designs and applications. TOSHIBA ASSUMES NO LIABILITY FOR CUSTOMERS' PRODUCT DESIGN OR APPLICATIONS.
- PRODUCT IS NEITHER INTENDED NOR WARRANTED FOR USE IN EQUIPMENTS OR SYSTEMS THAT REQUIRE EXTRAORDINARILY HIGH LEVELS OF QUALITY AND/OR RELIABILITY, AND/OR A MALFUNCTION OR FAILURE OF WHICH MAY CAUSE LOSS OF HUMAN LIFE, BODILY INJURY, SERIOUS PROPERTY DAMAGE AND/OR SERIOUS PUBLIC IMPACT ("UNINTENDED USE"). Except for specific applications as expressly stated in this document, Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the aerospace industry, lifesaving and/or life supporting medical equipment, equipment used for automobiles, trains, ships and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators and escalators, and devices related to power plant. IF YOU USE PRODUCT FOR UNINTENDED USE, TOSHIBA ASSUMES NO LIABILITY FOR PRODUCT. For details, please contact your TOSHIBA sales representative or contact us via our website.
- Do not disassemble, analyze, reverse-engineer, alter, modify, translate or copy Product, whether in whole or in part.
- Product shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable laws or regulations.
- The information contained herein is presented only as guidance for Product use. No responsibility is assumed by TOSHIBA for any infringement of patents or any other intellectual property rights of third parties that may result from the use of Product. No license to any intellectual property right is granted by this document, whether express or implied, by estoppel or otherwise.
- ABSENT A WRITTEN SIGNED AGREEMENT, EXCEPT AS PROVIDED IN THE RELEVANT TERMS AND CONDITIONS OF SALE FOR PRODUCT, AND TO THE MAXIMUM EXTENT ALLOWABLE BY LAW, TOSHIBA (1) ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (2) DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.
- Do not use or otherwise make available Product or related software or technology for any military purposes, including without limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile technology products (mass destruction weapons). Product and related software and technology may be controlled under the applicable export laws and regulations including, without limitation, the Japanese Foreign Exchange and Foreign Trade Law and the U.S. Export Administration Regulations. Export and re-export of Product or related software or technology are strictly prohibited except in compliance with all applicable export laws and regulations.
- Please contact your TOSHIBA sales representative for details as to environmental matters such as the RoHS compatibility of Product. Please
  use Product in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including
  without limitation, the EU RoHS Directive. TOSHIBA ASSUMES NO LIABILITY FOR DAMAGES OR LOSSES OCCURRING AS A RESULT
  OF NONCOMPLIANCE WITH APPLICABLE LAWS AND REGULATIONS.

# **TOSHIBA ELECTRONIC DEVICES & STORAGE CORPORATION**

https://toshiba.semicon-storage.com/

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Buffers & Line Drivers category:

Click to view products by Toshiba manufacturer:

Other Similar products are found below :

LXV200-024SW 74AUP2G34FW3-7 HEF4043BP NLU1GT126CMUTCG PI74FCT3244L MC74HCT365ADTR2G Le87401NQC Le87402MQC 028192B 042140C 051117G 070519XB NL17SZ07P5T5G NLU1GT126AMUTCG 74AUP1G17FW5-7 74LVC2G17FW4-7 CD4502BE 5962-8982101PA 5962-9052201PA 74LVC1G125FW4-7 NL17SH17P5T5G NL17SH125P5T5G NLV37WZ07USG RHRXH162244K1 74AUP1G34FW5-7 74AUP1G07FW5-7 74LVC2G126RA3-7 NLX2G17CMUTCG 74LVCE1G125FZ4-7 Le87501NQC 74AUP1G126FW5-7 TC74HC4050AP(F) 74LVCE1G07FZ4-7 NLX3G16DMUTCG NLX2G06AMUTCG NLVVHC1G50DFT2G NLU2G17AMUTCG LE87100NQC LE87290YQC LE87290YQCT LE87511NQC LE87511NQCT LE87557NQC LE87557NQCT LE87614MQC LE87614MQCT 74AUP1G125FW5-7 NLU2G16CMUTCG MC74LCX244MN2TWG NLV74VHC125DTR2G