



Part Number	TO COMPLETE PART NUMBER			
	A Diam.	B Height	C Diam.	D Depth
406R__	.625	.813	.458	.120
407R__	.720	.813	.520	.120
409R__	.875	.813	.660	.120
412R__	1.250	.813	1.041	.120

Shaft Hole
1 = 1/8"
2 = 1/4"




Part Number	TO COMPLETE PART NUMBER				
	A Diam.	B Height	C Diam.	D Depth	E Dial Diam.
406D__	.625	.813	.925	.120	.925
407D__	.720	.813	.520	.120	1.050
409D__	.875	.813	.660	.120	1.270
412D__	1.250	.813	1.041	.120	1.710

Shaft Hole
1 = 1/8"
2 = 1/4"




Part Number	TO COMPLETE PART NUMBER					
	A Diam.	B Height	C Diam.	D Depth	E Width	H Swing
406P__	.625	.813	.458	.120	1.223	.910
407P__	.720	.813	.520	.120	1.480	1.120
409P__	.875	.813	.660	.120	1.813	1.375
412P__	1.250	.813	1.041	.120	2.625	2.000

Shaft Hole
1 = 1/8"
2 = 1/4"




Part Number	TO COMPLETE PART NUMBER					
	A Diam.	B Height	C Diam.	D Depth	E Dial Diam.	H Swing
406PD__	.625	.813	.458	.120	1.373	.910
407PD__	.720	.813	.520	.120	1.645	1.120
409PD__	.875	.813	.660	.120	2.010	1.375
412PD__	1.250	.813	1.041	.120	2.855	2.000

Shaft Hole
1 = 1/8"
2 = 1/4"



Part Number	TO COMPLETE PART NUMBER				
	A Diam.	B Height	C Diam.	D Depth	E Swing
409PC2B	.875	.813	.660	.120	1.375
412PC2B	1.250	.813	1.041	.120	2.000

Shaft Hole
1 = 1/8"
2 = 1/4"



Part Number	TO COMPLETE PART NUMBER					
	A Diam.	B Height	C Diam.	D Depth	E Width	H Swing
409PDC2B	.875	.813	.660	.120	2.010	1.375
412PDC2B	1.250	1.540	1.041	.120	2.855	2.000

Shaft Hole
1 = 1/8"
2 = 1/4"

**ORDERING GUIDE FOR INDUSTRIAL SERIES**

Approximate Diameter	Style	Shaft Hole	Color
406 - 5/8"	R - Round	1 - 1/8"	B - Black Matte
407 - 3/4"	RWD - w/Dot (Round only)	2 - 1/4"	S - Black
409 - 7/8"	D - Round/Dial Skirt w/Arrow		Custom Colors and Custom Materials avail. by request
412 - 1 1/4"	P - Bar Pointer PD - Bar Pointer/Dial Skirt w/Arrow		

All Industrial Series knobs come standard with 2 set screws.

Approximate Diameter	Style	Shaft Hole	Color
5/8"	Round	.250"	B - Black Matte
<b>406</b>	<b>R</b>	<b>2</b>	<b>B</b>

EXAMPLE: 406-R-2B



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [ehc manufacturer](#):*

Other Similar products are found below :

[PVS-25B-2](#) [3488-2B](#) [DS125-6-2G](#) [MS91528-0E1B](#) [EH71-1P2S](#) [MS91528-2E2B](#) [PV-32B-2](#) [MS91528-OD1B](#) [EH71-4C2S](#) [MS91528-3F2B](#)  
[409P2B](#) [3489-1-B](#) [MS91528-1K2S](#) [PB-12B-1](#) [EH71-3F2S](#) [EH71-0K1S](#) [407R2B](#) [MS91528-3R2B](#) [409D2B](#) [EH71-1DSB2S](#) [EH71-4E2S](#)  
[409PD2B](#) [EH71-0C1S](#) [MS91528-1K1B](#) [EH710NP1S](#) [EH71-1D2S](#) [MS91528-4S2B](#) [EH71-3C2S](#) [MS91528-1B2B](#) [3442-2-B](#) [3441-2-B](#) [3440-](#)  
[1-B](#) [MS91528-4F2B](#) [EH71-2C2S](#) [3008-1-B](#) [PC1F2B](#) [407D2B](#) [MS91528-0F1B](#) [MS91528-1D1B](#) [MS91528-2F2B](#) [MS91528-1D2B](#)  
[MS91528-1II2B](#) [MS91528-1F2S](#) [MS91528-1P2S](#) [3010-2-B](#) [EH712F2S](#) [EH71-2P2S](#) [MS91528-2P2B](#) [MS91528-2D2B](#) [EH71-1GG2S](#)