



Key Features

- Quad band GSM & 3G
- ISM: 868 and 915MHz
- 56mm
- SMA male connector
- Groundplane independent
- RoHS compliant

General Description

The Delta 1A Multiband antenna combines good performance in a small size, enabling its use with many of today's GSM / GPRS, 3G and ISM products.

Terminated with an SMA male connector, it is ideally suited to applications requiring a simple, cable free set up, such as Point of Sale, metering or alarm panel equipment; as well as being a popular addition to radio manufacturers evaluation kits.

The omni directional, radiating element is over moulded in black high-grade rubber which allows flexibility and provides a rugged stylish finish, ensuring years of reliable use.

The Delta 1A is a popular antenna for customers requiring a straightforward to fit, versatile product, that is qualified and used with many of today's GSM / GPRS and 3G / UMTS terminals and manufacturers of wireless communication equipment.

Additional Considerations

- Ensures antenna can be discretely mounted
- Fits to many popular GSM / GPRS and 3G / UMTS terminal equipment
- Does not rely on mounting on metallic surface
- Meets all EU compliance criteria for electronic goods


Rev 1.3

Key Specifications - Electrical

Operating temperature range:	-20 to +60°C
Storage temperature range:	-30 to +75°C
Impedance:	50 ohm
Gain:	2.0dBi
VSWR:	2.0 Max
Operating frequencies:	GSM: 800, 900, 1800, 1900MHz 3G: 2100MHz ISM: 868, 915MHz
Radiation:	Omni

Key Specifications - Mechanical

Dimensions:	56mm
Connector:	SMA male
Mounting method:	Direct connect
Connector plating:	Gold/Nickel



Ordering Details

Part Number	Description
DELTA1A/X/SMAM/S/S	Stubby Quad Band GSM & 3G Antenna, SMA Male

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [SIRETTA](#) manufacturer:

Other Similar products are found below :

[ALPHA4A/5M/SMAM/S/S/26](#) [DELTA5A/X/SMAM/S/S/17](#) [OSCAR17/X/TNC/S/S/19](#) [DELTA5A/X/BNCM/S/S/17](#) [SNYPER-LTE-SPECTRUM](#) [ASMA2000F058L13](#) [ASMA2000C058L13](#) [TANGO14/5M/LL/SMAM/S/S/24](#) [TANGO1/1M/FMEF/S/S/4](#) [ASME500F058L13](#) [TANGO3/0.5M/SMAM/S/S/31](#) [TANGO40/X/NTYPEF/S/S/32](#) [QUARTZ-W22-LTE\(EU\)+ACC](#) [ASMA500B174L13](#) [31557](#) [ECHO40/0.1M/UFL/S/S/32](#) [MIKE1A/5M/FMEF/S/S/20](#) [QUARTZ-W22-UMTS\(EU\)+ACC](#) [TANGO11A/2.5M/SMAM/S/S/19](#) [ASMA500F058L13](#) [ZETA-N-UMTS](#) [ECHO11/0.2M/IPEX/S/S/12](#) [ASMA300E174L13](#) [ASMA1000F058L13](#) [DELTA19/X/SMAM/S/S/35](#) [ASMA2000E058L13](#) [ASMZG300F058L13](#) [MIKE3A/5M/SMAM/S/S/17](#) [TANGO15/3M/SMAM/SMAM/S/S/24](#) [TANGO20/3M/SMAM/S/S/26](#) [ASMZG500A058L13](#) [ASMZG1500F058L13](#) [ALPHA1A/2.5M/SMAM/S/S/11](#) [OSCAR40/10M/LL/SMAM/S/S/33](#) [TANGO11A/5M/LL/SMAM/S/S/19](#) [TANGO29/1M/SMAM/RP/S/35](#) [ASME2000F058L13](#) [ASMK015X174S11](#) [LC300-N2-GPRS](#) [DELTA6A/X/SMAM/S/S/11](#) [MIKE1A/2.5M/FMEF/S/S/20](#) [ASMZG1000F058L13](#) [OSCAR41/X/NTYPEF/S/S/29](#) [TANGO22/3M/SMAM/SMAM/SMAM/26](#) [OSCAR420/0.4M/NTYPEF/S/S/19](#) [ASMK010X174S11](#) [ZETA-N2-GPRS](#) [ADAPT/SMAM/RP](#) [OSCAR18/X/NF/S/S/22](#) [TANGO14/3M/SMAM/S/S/24](#)