



Representative Image

**Alternate Catalog No. SU203M-C50**  
**Catalog No. 2CDS273337R0504**

**Description:** UL489 MCB 3P C 50A 240

**UPC No** 4016779931403

**Home > Modular DIN Rail Products > Mini Circuit breakers**

SU203M-C50 Miniature Circuit Breaker C-Char., 10kA, 50A, 3P UL489

## Descriptors

|          |                       |
|----------|-----------------------|
| Category | Mini Circuit breakers |
|----------|-----------------------|

## Specifications

|                                                |                                                        |
|------------------------------------------------|--------------------------------------------------------|
| Interrupting Rating acc. to UL489              | (240 V AC) 10 kA<br>(96 V DC) 10 kA                    |
| Number of Poles                                | 3                                                      |
| Power Loss                                     | 13,5 W<br>at Rated Operating Conditions per Pole 4,5 W |
| Product Main Type                              | SU200M                                                 |
| Rated Current                                  | 50 A                                                   |
| Rated Ultimate Short-Circuit Breaking Capacity | (400 V AC) 15 kA                                       |
| Rated Voltage (V)                              | (240 V AC)<br>(96 V DC)                                |
| Standards                                      | CSA 22.2 No. 5<br>IEC/EN 60947-2<br>UL 489             |
| Tripping Characteristic                        | C                                                      |

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Circuit Breakers](#) category:*

*Click to view products by [ABB](#) manufacturer:*

Other Similar products are found below :

[M39019/01-201](#) [M55629/1-046](#) [M55629/1-079](#) [M55629/1-109](#) [M55629/5-078](#) [M55629/5-101](#) [GFR5352OWA](#) [9926252830](#) [122-215-101](#)  
[1393247-5](#) [1423371-1](#) [AP112-23206-1](#) [AP112-4845-2](#) [AP112-78-23](#) [AP117-33420-1](#) [AP117-4162-17](#) [AP13-1874-2](#) [AP17-33695-25](#) [AP1-](#)  
[87054-011](#) [AP6-1RC-5995-008](#) [AP7-1R-37518-1](#) [APGN662-22892-1](#) [IALHK11-26827-1](#) [IEGBX1-35204-10L-V](#) [IEGH11-35886-2-V](#)  
[IEGHS66-1-62F-18.0-01-V](#) [IEGS1-1REC4-52F-8.00-S-61-](#) [IEGZXF6-32318-30-V](#) [IEL1-28878-2](#) [IELHK112-26767-11-V](#) [IELK1-1REC4R-](#)  
[31793-70](#) [IELR11-26886-6](#) [IELXK1111-1REC5-39457-10-V](#) [IMLHK11-1-52-15.0-01](#) [IMLK1-33032-6](#) [IPA-66-1REG4-62-.500-01](#) [203-1-1-](#)  
[52-902-1-1](#) [203-2-1-51-102-5-1-8](#) [203-2-1-52-103-6-1-8](#) [203-2-1-62-252-4-1-1](#) [203-2-1-64-502-4-1-13](#) [203-2-1-65-153-4-1-1](#) [203-2-1-65-](#)  
[203-6-1-10](#) [203-2-1-66-103-4-1-1](#) [203-22-1-42-252-5-1-5](#) [203-22-14-2740-7](#) [203-22-1-61-203-4-1-1](#) [203-22-1-62F-103-4-3-13](#) [203-22-1-62F-](#)  
[502-4-1-1-A](#) [203-222-1-41-752-4-1-13](#)