



Representative Image

## Catalog No. THQB2120

**Description:** THQB MCB 20A 10KA 2P 120/240V

**UPC No** 783164012248

**Home > Circuit Breakers > Miniature Circuit Breakers > Q-Line Miniature Circuit Breakers**

Q line circuit breakers are one-inch wide per pole, compact, thermal-magnetic devices designed for residential and commercial applications. The QB breakers are bolt-on versions of the Q Line used for bolting to the bus connections of load centers and lighting panels. All Q Line circuit breakers feature Quick-make / Quick-break mechanisms, common trip bars, and easy to spot trip indication to ensure safety and reliability. Q Line breakers are available in 1, 2, and 3 pole versions, can be ordered with auxiliary contact and shunt trip accessories, and can be ordered for use in HID applications. 2120 Amps 20 A

### Descriptors

|              |                                   |
|--------------|-----------------------------------|
| Category     | Q-Line Miniature Circuit Breakers |
| Product Line | TEY / Q-Line (Bolt-On)            |
| GO Schedule  | EB                                |

### Specifications

|                                 |                         |
|---------------------------------|-------------------------|
| Trip Style                      | Non-Interchangeable     |
| Frame Type                      | Q-Line                  |
| Amperage                        | 20 A                    |
| System Voltage                  | 120 Vac<br>120/240 Vac  |
| Poles                           | 2                       |
| Trip Function                   | LI                      |
| Continuous Current Rated        | Standard                |
| 120 Vac Interrupting Rating     | 10 KAIC                 |
| 120/240 Vac Interrupting Rating | 10 KAIC                 |
| Suitable for Reverse Feed       | Yes                     |
| Wire Range (Cu/Al)              | 14-8 kcmil / 12-8 kcmil |
| Long Time                       | Fixed                   |
| Instantaneous                   | Fixed                   |
| Protective Relays               | No                      |
| Current Metering                | No                      |
| Special Markings                | HACR                    |
| GSA Compliance                  | Yes                     |

### Classifications

|           |        |
|-----------|--------|
| UL File # | E11592 |
|-----------|--------|

**by ABB**

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Circuit Breakers](#) category:*

*Click to view products by [ABB](#) manufacturer:*

Other Similar products are found below :

[M39019/01-201](#) [M55629/1-046](#) [M55629/1-079](#) [M55629/1-109](#) [M55629/5-078](#) [M55629/5-101](#) [GFR5352OWA](#) [9926252830](#) [122-215-101](#)  
[1393247-5](#) [1423371-1](#) [AP112-23206-1](#) [AP112-4845-2](#) [AP112-78-23](#) [AP117-33420-1](#) [AP117-4162-17](#) [AP13-1874-2](#) [AP17-33695-25](#) [AP1-](#)  
[87054-011](#) [AP6-1RC-5995-008](#) [AP7-1R-37518-1](#) [APGN662-22892-1](#) [IALHK11-26827-1](#) [IEGBX1-35204-10L-V](#) [IEGH11-35886-2-V](#)  
[IEGHS66-1-62F-18.0-01-V](#) [IEGS1-1REC4-52F-8.00-S-61-](#) [IEGZXF6-32318-30-V](#) [IEL1-28878-2](#) [IELHK112-26767-11-V](#) [IELK1-1REC4R-](#)  
[31793-70](#) [IELR11-26886-6](#) [IELXK1111-1REC5-39457-10-V](#) [IMLHK11-1-52-15.0-01](#) [IMLK1-33032-6](#) [IPA-66-1REG4-62-.500-01](#) [203-1-1-](#)  
[52-902-1-1](#) [203-2-1-51-102-5-1-8](#) [203-2-1-52-103-6-1-8](#) [203-2-1-62-252-4-1-1](#) [203-2-1-64-502-4-1-13](#) [203-2-1-65-153-4-1-1](#) [203-2-1-65-](#)  
[203-6-1-10](#) [203-2-1-66-103-4-1-1](#) [203-22-1-42-252-5-1-5](#) [203-22-14-2740-7](#) [203-22-1-61-203-4-1-1](#) [203-22-1-62F-103-4-3-13](#) [203-22-1-62F-](#)  
[502-4-1-1-A](#) [203-222-1-41-752-4-1-13](#)