

Energy Harvester SPGA Series

**No power supply, battery or maintenance required.
Power generated with a low-force push.**

The SPGA Series Energy Harvester is a compact power-generating device employing electromagnetic induction to generate power with each push or release. Combined with low-power wireless technology, the device can function as a switch. It can be installed away from a main board, for example, in places where connection to a power source, or battery replacement, is difficult, and is ideal particularly for frequently operated equipment.



SPGA Series

Features

- Long operating life of 1 million cycles
- Excellent feel achieved with operating force of 6±1.5N
- Compact dimensions (17.5 × 23 × 17.9mm)


Applications

- Equipment with batteries in danger of going flat at the wrong time
- Operation, position sensing in places where circuitry or wiring is complicated
- Can be retrofitted to existing equipment as wiring not required


Items		Specifications	
Part number		SPGA110100	
Dimensions (W×D×H)		17.5×23×17.9mm	
Power generation		170μJ (for each operation)	
Operating force		6N±1.5N	
Travel		3.3mm	
Operation		Push	
Poles		1	
Terminal type		For PC board	
Operating temperature range		-20°C to +70°C	
Mechanical performance	Actuator strength	Operating direction	35N
		Perpendicular direction	5N
Durability	Operating life	1,000,000 cycles	
Environmental performance	Cold	-40°C 96h	
	Dry heat	85°C 96h	
	Damp heat	60°C, 90 ~ 95%RH 96h	
3D CAD (STEP)		↓	
Certificate of Compliance to RoHS regulations		↓	

※ Please contact an Alps Alpine sales representative about wireless systems, auxiliary circuits or other inquiries.

Dimensions



Mounting Hole Dimensions



Packing Specifications

Tray		
Number of packages (pcs.)	1 case / Japan	320
	1 case / export packing	320
Export package measurements (mm)	360×270×230	

Soldering Conditions

Reference for Hand Soldering	
Soldering temperature	350±5°C
Soldering time	3s max.

Products

- Products News
- Search by Application
- Search by Specs
- Product Basics
- PDF Catalog
- 3D CAD/RoHS Directives Support
- Sensors
- Switches
- TACT Switch™
- Contactsheet™
- Encoders
- Potentiometers
- Multi Control Devices
- Connectors
- Aspherical Glass Lens
- Communication Modules
- Power Inductors
- Current Sensor
- Toroidal Coil
- Touch Input Devices
- Actuators
- HAPTIC™ Reactor
- Printer
- Deleted Products

Alps Company Info

- Top Message
- Global Network
- Overview of Business Operations
- Technology
- News Releases

News Releases

- 2019
- 2018
- 2017
- 2016
- 2015

CSR Environment

- Top Message
- Alps Business Approach
- Alps Philosophy
- Relations with Customers
- Environmental Preservation
- Relations with Employees
- Relations with Suppliers
- Fair Management
- Social Contribution
- CSR Management
- CSR Library

Investor Relations

- Consolidated Financial Statements
- IR Calendar
- IR Library
- Stock Information
- General Meeting of Shareholders
- Careers**
- Opportunities and Jobs
- IAP - Job offer
- International Associates Program
- FAQ

About ALPS

- History
- Alps Company (former Alps Electric) by Video

Other

- Terms of Use
- Privacy Policy
- About the trademarks
- Contact Us

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Limit Switches](#) category:

Click to view products by [ALPS](#) manufacturer:

Other Similar products are found below :

[5ML1-E1](#) [5ML31](#) [LZG1](#) [LZL1-6C](#) [622EN114-R](#) [622EN18-6](#) [622EN224-6B](#) [622EN230](#) [622EN237-R](#) [622EN69-3](#) [622EN85-RB](#) [MA-10019](#)
[6PA109](#) [7LS51](#) [83547001](#) [83725002](#) [83830001](#) [83840701](#) [83841001](#) [83881140](#) [8AS42](#) [8LS10](#) [8LS125-4PG](#) [8LS152-4PGN20](#) [914CE16-](#)
[3A](#) [914CE3-3L1](#) [915PA10](#) [91MCE16-P2O](#) [924CE16-Y3](#) [924CE1-S6](#) [924CE1-T25A](#) [924CE1-T3](#) [924CE1-T9A](#) [924CE2-T9](#) [924CE31-Y20-](#)
[X5](#) [924CE31-Y3L1](#) [GL-10054](#) [GLAB26J2B](#) [GLDB03C-6](#) [GLDC05C](#) [PS21R-NT11N7-YK0](#) [H3141CAKAA](#) [RDI-G-L5B](#) [DD-10000](#) [DT-](#)
[2R3-A7](#) [14CE16-3N28](#) [14CE18-N15](#) [151ML3-E1](#) [E3102BAAAA](#) [BFL1-AW1-S](#)