

AFBR-TUS500Z

Transparent Jacket Plastic Optical Fiber

AVAGO
TECHNOLOGIES

Data Sheet



Cable description

The AFBR-TUS500Z plastic fiber optic cable is constructed of a single step-index fiber sheathed in a transparent polyethylene jacket. The cable is supplied in spools of 500m.




Figure 1. Typical POF attenuation vs. wavelength

Features

- Compatible with Avago Versatile Link Family of connectors and fiber optic components
- 1.0/2.2 mm diameter Plastic Optical Fiber (POF) with 0.21dB/m typical attenuation (-40°C to 85°C)
- PMMA core
- Fluorinated polymer cladding
- Transparent polyethylene jacket
- Halogen free

Applications

- Arc flash event detection
- Light detection




Figure 2. AFBR-TUS500Z structure

Plastic Optical Fiber Specifications: AFBR-TU5500Z

Absolute Maximum Ratings

Parameter	Symbol	Min.	Max.	Unit	Note
Recommended storage Temperature	T _S	-55	+85	°C	
Recommended Operating Temperature	T _O	-40	+85	°C	
Recommended Installation Temperature	T _i	0	+70	°C	1
Short Term Tensile Force	F _T		50	N	2, 3
Long Term Tensile Load	F _T		1	N	2, 4
Bend Radius	r	30		mm	5, 6, 7
Humidity range	H		85	%	

Mechanical Characteristics, T_A = -40°C to +85°C unless otherwise specified

Parameter	Symbol	Min.	Typ.	Max.	Unit	Note
Numerical Aperture	NA		0.48			8
Diameter Core and Cladding	DC	0.94	1.00	1.06	mm	
Diameter Jacket	DJ	2.13	2.20	2.27	mm	
Refractive Index	n		1.492			
Core			1.412			
Cladding						
Mass per Unit Length			3.7		g/m	9

Optical Characteristics, T_A = -40°C to +85°C unless otherwise specified

Parameter	Symbol	Min.	Typ.	Max.	Unit	Note
Cable Attenuation	α ₀	0.16	0.21	0.26	dB/m	
Source: 650nm, LED, NA=0.5 (Source: AFBR-1529Z)						
Capturing constant	C		3E-9		m	10
Propagation delay constant	I/v		5		ns/m	11

Notes:

1. Installation temperature is the range over which the cable can be bent and pulled without damage. Below 0°C the cable becomes brittle and should not be subjected to mechanical stress.
2. Fail criteria for tensile force test: elongation higher than 5% of original length.
3. Short term: 30mins.
4. Long term: 24hours
5. Bend angle is 90°. Bend radius is the radius of the mandrel around which the cable is bent.
6. Fail criteria for bend radius test: increase in attenuation higher than 0.5dB.
7. Test duration: 24hours.
8. Fiber length longer than 2 meters
9. Without connectors
10. The optical power P at the photo detector can be calculated as $P = C * L * E / K$ with;
 - P: Optical power on detector [W]
 - C: Capturing constant [m]
 - L: Illuminated length of fiber [m]
 - E: Optical power density in illuminated area [W/m²], halogen lamp used as light source
 - K: Correction factor for transmission losses [1], calculated as: $K=10^{(A*L2/10)}$
 - A: Transmission loss [dB/m]
 - L2: Length of fiber between illuminated area and photo detector [m], i.e. wiring length.
 - * Capturing constant determined with a fiber length of 12m.
11. Propagation delay constant is the reciprocal of the group velocity for propagation delay of optical power. Group velocity is $v=c/n$, where c is the velocity of light in free space (3×10^8 m/s) and n is the effective core index of refraction.

For product information and a complete list of distributors, please go to our web site: www.avagotech.com

Avago, Avago Technologies, and the A logo are trademarks of Avago Technologies in the United States and other countries.

Data subject to change. Copyright © 2005-2015 Avago Technologies. All rights reserved.

AV02-4965EN - July 6, 2015



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Fibre Optic Cables category:

Click to view products by Broadcom manufacturer:

Other Similar products are found below :

[FPD01SBS200](#) [FPD06SCC200](#) [FPT01SBS200](#) [FPDK01SCC100](#) [FCS-HCP-DUPLEX-50M](#) [FOSP45-C](#) [FURA3-20](#) [FURA4-20/A](#) [FURD3-20/A](#) [FURD4-20/A](#) [FURO6-20/A](#) [FUTA3-20](#) [FUTA3-20/A](#) [FUTA4-20](#) [FUTA4-20/A](#) [FUTD3-20/A](#) [FUTD4-20/A](#) [FUTO3-20/A](#) [FUTS3-20](#) [FUTS3-20/A](#) [FUTS4-20](#) [FUTS4-20/A](#) [943-99595-10030](#) [FUT-FARR25-20](#) [HFBR-RUD100](#) [2799445](#) [28320002](#) [28030002](#) [28051002](#) [28052002](#) [28351002](#) [28320001](#) [28020001](#) [AERO-AS04-012-A-0X12026BKTT](#) [AERO-DF03-002-D-0XC18TT](#) [HFBR-EUS100Z](#) [HFBR-RUS100Z](#) [ER-500-1-VC-DCY-02-D0-0LWD](#) [EXO-G0-04-A-0LC32BKTT](#) [EXO-G0-08-A-0LC32GYTT](#) [EXO-G0-12-A-0XC32BKTT](#) [EXO-G0-24-A-0XC32BKTT](#) [MK-AX2-04-SM2](#) [106800-0100](#) [106800-0105](#) [106800-0059](#) [106800-0064](#) [106803-1003](#) [106803-1004](#) [106803-2040](#)