


SR1030-G Thru. SR10200-G

Forward current: 10A

Reverse voltage: 30 to 200V

RoHS Device




Features

- Metal of silicon rectifier , majority carrier conduction.
- Guard ring for transient protection.
- Low Power Loss / High Efficiency.
- High current capability , low VF.
- High surge capacity.
- For use in low voltage , high frequency inverters , free wheeling, and polarity protection applications.

Mechanical data

- Case: TO-220AC, molded plastic.
- Epoxy: UL 94V-0 rate flame retardant.
- Polarity: As marked on the body.
- Mounting position: Any
- Weight: 2.24 grams



Maximum Ratings and Electrical Characteristics

Ratings at 25°C ambient temperature unless otherwise specified.
Single phase, half wave, 60Hz, resistive or inductive load.
For capacitive load derate current by 20%.

| Characteristics | Symbol | SR10 30-G | SR10 40-G | SR10 50-G | SR10 60-G | SR10 80-G | SR10 100-G | SR10 150-G | SR10 200-G | Unit | | | | |
|---|-------------------|--------------|--------------|--------------|--------------|--------------|---------------|---------------|---------------|------|--|--|--|--|
| Maximum recurrent peak reverse voltage | V _{RRM} | 30 | 40 | 50 | 60 | 80 | 100 | 150 | 200 | V | | | | |
| Maximum RMS voltage | V _{RMS} | 21 | 28 | 35 | 42 | 56 | 70 | 105 | 140 | V | | | | |
| Maximum DC blocking voltage | V _{DC} | 30 | 40 | 50 | 60 | 80 | 100 | 150 | 200 | V | | | | |
| Maximum average forward rectified current (See Fig.1) @T _J =95°C | I _(AV) | 10.0 | | | | | | | | A | | | | |
| Peak forward surge current, 8.3ms single half sine-wave super imposed on rated load (JEDEC method) | I _{FSM} | 175 | | | | | | | | A | | | | |
| Peak forward voltage at 10.0A DC (Note 1) | V _F | 0.55 | | 0.70 | | 0.85 | | 0.95 | | V | | | | |
| Maximum DC reverse current @T _J =25°C at rated DC blocking voltage @T _J =100°C | I _R | 1.0 50 | | | | | | | | mA | | | | |
| Typical junction capacitance (Note 2) | C _J | 500 | | | | | | | | pF | | | | |
| Typical thermal resistance (Note 3) | R _{θJC} | 2.5 | | | | | | | | °C/W | | | | |
| Operating temperature range | T _J | -55 ~ +125 | | | | | | | | °C | | | | |
| Storage temperature range | T _{STG} | -55 ~ +150 | | | | | | | | °C | | | | |

NOTES: 1. 1.300us pulse width,2% duty cycle.
2. Measured at 1.0MHz and applied reverse voltage of 4.0V DC.
3. Thermal resistance junction to case.

Company reserves the right to improve product design , functions and reliability without notice.

REV:B

RATING AND CHARACTERISTIC CURVES (SR1030-G Thru. SR10200-G)

Fig.1 Forward Current Derating Curve




Fig.2 Max. Non-repetitive Surge Current




Fig.3 Typical Reverse Characteristics




Fig.4 Typical Forward Characteristics





Fig.5 Typical Junction Capacitance




Company reserves the right to improve product design , functions and reliability without notice.

REV:B

Marking Code

| Part Number | Marking code |
|-------------|--------------|
| SR1030-G | SR1030 |
| SR1040-G | SR1040 |
| SR1050-G | SR1050 |
| SR1060-G | SR1060 |
| SR1080-G | SR1080 |
| SR10100-G | SR10100 |
| SR10150-G | SR10150 |
| SR10200-G | SR10200 |



C = Comchip Logo
XXX = Product type marking code

Standard Packaging

| Case Type | TUBE PACK | |
|-----------|-----------------|----------------|
| | TUBE (pcs) | BOX (pcs) |
| TO-220AC | 50 | 2,000 |

Company reserves the right to improve product design , functions and reliability without notice.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Schottky Diodes & Rectifiers category:

Click to view products by Comchip manufacturer:

Other Similar products are found below :

[MA4E2039](#) [D1FH3-5063](#) [MBR10100CT-BP](#) [MBR1545CT](#) [MMBD301M3T5G](#) [RB160M-50TR](#) [RB551V-30](#) [BAS16E6433HTMA1](#) [BAT54-02LRH](#) [E6327](#) [NSR05F40QNXT5G](#) [NTE555](#) [JANS1N6640](#) [SB07-03C-TB-H](#) [SK310-T](#) [SK32A-LTP](#) [SK33A-TP](#) [SK34B-TP](#) [SS3003CH-TL-E](#) [GA01SHT18](#) [CRS10I30A\(TE85L,QM](#) [MA4E2501L-1290](#) [MBRA140TRPBF](#) [MBRB30H30CT-1G](#) [SB007-03C-TB-E](#) [SK32A-TP](#) [SK33B-TP](#) [SK35A-TP](#) [SK38B-TP](#) [NRVBM120LT1G](#) [NTE505](#) [NTSB30U100CT-1G](#) [SS15E-TP](#) [VS-6CWQ10FNHM3](#) [ACDBA1100LR-HF](#) [ACDBA1200-HF](#) [ACDBA140-HF](#) [ACDBA2100-HF](#) [ACDBA3100-HF](#) [CDBQC0530L-HF](#) [CDBQC0240LR-HF](#) [BAT6202VH6327XTSA1](#) [ACDBA340-HF](#) [ACDBA260LR-HF](#) [ACDBA1100-HF](#) [SK310B-TP](#) [MA4E2502L-1246](#) [MA4E2502H-1246](#) [NRVBM120ET1G](#) [NSR01L30MXT5G](#) [NTE573](#)