

SR320U THRU SR3250U

3.0 AMP. Schottky Barrier Rectifiers

Features

Plastic package has Underwriters Laboratory
 Flammability Classification 94V-0 utilizing
 Flame Retardant Epoxy Molding Compound.

- Guard ring for overvoltage protection
- · High current capability, low forward voltage drop
- · Low power loss, high efficiency
- High surge capability

Mechanical Data


Case: Molded plastic DO-201AD

 Terminals: Plated leads solderable per MIL-STD-202, Method 208 guaranteed

· Polarity: Color band dentes cathode end

Mounting Position: AnyMaking: Type Number

· Lead Free: For RoHS/Lead Free Version



Dimensions in inches and (millimeters)

Maximum Ratings and Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified

Single phase, half wave, 60Hz, resistive or inductive load

For capacitive load derate current by 20%

Type Number	SYMBOL	SR 320U	SR 330U	SR 340U	SR 345U	SR 350U	SR 360U	SR 380U	SR 3100U	SR 3150U	SR 3200U	SR 3250U	Unit
Maximum Recurrent Peak Reverse Voltage	VRRM	20	30	40	45	50	60	80	100	150	200	250	V
Maximum RMS Voltage	VRMS	14	21	28	31.5	35	42	56	70	105	140	175	V
Maximum DC Blocking Voltage	VDC	20	30	40	45	50	60	80	100	150	200	250	V
Average Rectified Output Current (Note 1) @TL=100°C	IF(AV)	3.0											Α
Peak Forward Surge Current 8.3ms Single half sine-wave superimposed on rated load (JEDEC Method)	I FSM	90											А
I ² t Rating for Fusing (t < 8.3ms)	l ² t	33.615											A ² s
Forward Voltage @IF=3.0A	V _{FM}	0.50 0.6				.67	0.8	0.82 0.		90	0.92	V	
Peak Reverse Current @T _A =25°C	l _R	0.1 0.05											m ^
At Rated DC Blocking Voltage @T _A =100°C	IR	10.0 5.0									mA		
Typical Junction Capacitance (Note 2)	Сı	140 80								pF			
Typical Thermal Resistance Junction to Ambient(Note 1)	Rejl Rejc Reja	10 12 45											°C/W
Operating Temperature Range	TJ	-55 to + 150											$^{\circ}$
Storage Temperature Range	Tstg	-55 to + 150											$^{\circ}$

Note: 1. Leads maintained at ambient temperature at a distance of 9.5mm from the case

2. Measured at 1.0 MHz and Applied reverse Voltage of 4.0V D.C

version:06 1 of 3



SR320U THRU SR3250U

3.0 AMP. Schottky Barrier Rectifiers

FIG.1- MAXIMUM FORWARD CURRENT DERATING CURVE




FIG.3- MAXIMUM NON-REPETITIVE FORWARD SURGE CURRENT




FIG.2- TYPICAL FORWARD CHARACTERISTICS





FIG.4- TYPICAL JUNCTION CAPACITANCE



PERCENT OF RATED PEAK REVERSE VOLTAGE (%)

version:06 2 of 3



SR320U THRU SR3250U

3.0 AMP. Schottky Barrier Rectifiers

Important Notice and Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from XINNUO
- XINNUO reserves the right to make changes to this document and its products and specifications
- XINNUO disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- XINNUO does not assume any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the here in document are examples of standard use and operation. Customers are responsible in comprehending the suitable use in particular applications.
 - XINNUO makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown here in are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own ris k andagree to fully indemnify XINNUO for any damages resulting from such improper use or sale.
- Since XINNUO uses lot number as the tracking base, please provide the lot number for tracking when complaining.

version:06 3 of 3

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Schottky Diodes & Rectifiers category:

Click to view products by DIYI manufacturer:

Other Similar products are found below:

MA4E2039 MMBD301M3T5G RB160M-50TR D83C BAS16E6433HTMA1 BAS 3010S-02LRH E6327 BAT 54-02LRH E6327

NRVBAF360T3G NSR05F40QNXT5G NTE555 JANS1N6640 SS3003CH-TL-E GA01SHT18 CRS10I30A(TE85L,QM MBRA140TRPBF

MBRB30H30CT-1G BAT 15-04R E6152 JANTX1N5712-1 DMJ3940-000 SB007-03C-TB-E NRVBB20100CTT4G NRVBM120LT1G

NTSB30U100CT-1G CRG04(T5L,TEMQ) ACDBA1100LR-HF ACDBA1200-HF ACDBA240-HF ACDBA3100-HF CDBQC0530L-HF

ACDBA260LR-HF ACDBA1100-HF 10BQ015-M3/5BT NRVBM120ET1G VSSB410S-M3/5BT 1N5819T-G PDS1040Q-13 B160BQ-13-F

SDM05U20CSP-7 BAS 70-07 E6433 B140S1F-7 HSM560Je3/TR13 DDB2265-000 ZHCS506QTA HSM190Je3/TR13 B330AF-13

ACDBUC0230-HF SDM1U100S1F-7 MBR10200CTF-G1 CDLL5712 DMF2822-000