


DIN 319


Ball knobs



DIN 319-C



DIN 319-E



technical informations

Material

- KU: phenolic based (PF) black Duroplast, glossy finish.
 - KU-C-RT: phenolic based (PF) red Duroplast, glossy finish available only with tapped blind hole.
 - KT: polyamide based (PA) black technopolymer, matte finish available only with tapped blind hole.
- Duroplast and technopolymer are resistant to solvents, oils, greases and other chemical agents.

Assembly

- Version C: tapped blind hole.
- Version E: with steel insert.

| Standard Elements | Main dimensions | | | Mounting hole | | Weight |
|------------------------|-----------------|------|----------------|---------------|------------------|--------|
| Description | D | L | d ₁ | d | h _{min} | g |
| DIN 319-KU-12-M4-C | 12 | 11.2 | 6 | M4 | 6.5 | 1 |
| DIN 319-KT-16-M4-C | 16 | 15 | 8 | M4 | 7 | 3 |
| DIN 319-KU-16-M4-C | 16 | 15 | 8 | M4 | 7 | 3 |
| DIN 319-KU-16-M4-C-RT | 16 | 15 | 8 | M4 | 7 | 3 |
| DIN 319-KU-16-M4-E | 16 | 15 | 8 | M4 | 6 | 3 |
| DIN 319-KT-16-M5-C | 16 | 15 | 8 | M5 | 7 | 3 |
| DIN 319-KU-16-M5-C | 16 | 15 | 8 | M5 | 7 | 3 |
| DIN 319-KU-16-M5-C-RT | 16 | 15 | 8 | M5 | 7 | 3 |
| DIN 319-KT-20-M5-C | 20 | 18 | 12 | M5 | 9 | 6 |
| DIN 319-KU-20-M5-C | 20 | 18 | 12 | M5 | 9 | 6 |
| DIN 319-KU-20-M5-C-RT | 20 | 18 | 12 | M5 | 9 | 6 |
| DIN 319-KT-20-M5-E | 20 | 18 | 12 | M5 | 7.5 | 9 |
| DIN 319-KU-20-M5-E | 20 | 18 | 12 | M5 | 7.5 | 9 |
| DIN 319-KT-20-M6-C | 20 | 18 | 12 | M6 | 9 | 6 |
| DIN 319-KU-20-M6-C | 20 | 18 | 12 | M6 | 9 | 5 |
| DIN 319-KU-25-M5-C | 25 | 22.5 | 15 | M5 | 11 | 10 |
| DIN 319-KT-25-M6-C | 25 | 22.5 | 15 | M6 | 11 | 10 |
| DIN 319-KU-25-M6-C | 25 | 22.5 | 15 | M6 | 11 | 10 |
| DIN 319-KU-25-M6-C-RT | 25 | 22.5 | 15 | M6 | 11 | 10 |
| DIN 319-KT-25-M6-E | 25 | 22.5 | 15 | M6 | 9 | 13 |
| DIN 319-KU-25-M6-E | 25 | 22.5 | 15 | M6 | 9 | 13 |
| DIN 319-KT-25-M8-C | 25 | 22.5 | 15 | M8 | 11 | 10 |
| DIN 319-KU-25-M8-C | 25 | 22.5 | 15 | M8 | 11 | 10 |
| DIN 319-KU-25-M8-E | 25 | 22.5 | 15 | M8 | 9 | 18 |
| DIN 319-KU-30-M8-C | 30 | 28 | 15 | M8 | 14.5 | 19 |
| DIN 319-KU-32-M6-C | 32 | 29 | 18 | M6 | 14.5 | 20 |
| DIN 319-KT-32-M8-C | 32 | 29 | 18 | M8 | 14.5 | 25 |
| DIN 319-KU-32-M8-C | 32 | 29 | 18 | M8 | 14.5 | 22 |
| DIN 319-KU-32-M8-C-RT | 32 | 29 | 18 | M8 | 14.5 | 22 |
| DIN 319-KT-32-M8-E | 32 | 29 | 18 | M8 | 12 | 22 |
| DIN 319-KU-32-M8-E | 32 | 29 | 18 | M8 | 12 | 22 |
| DIN 319-KT-32-M10-C | 32 | 29 | 18 | M10 | 14.5 | 22 |
| DIN 319-KU-32-M10-C | 32 | 29 | 18 | M10 | 14.5 | 22 |
| DIN 319-KU-35-M10-C | 35 | 32.5 | 18 | M10 | 18 | 29 |
| DIN 319-KU-35-M10-C-RT | 35 | 32.5 | 18 | M10 | 18 | 28 |
| DIN 319-KU-40-M8-C | 40 | 37 | 22 | M8 | 18 | 35 |
| DIN 319-KT-40-M10-C | 40 | 37 | 22 | M10 | 18 | 43 |
| DIN 319-KU-40-M10-C | 40 | 37 | 22 | M10 | 18 | 43 |
| DIN 319-KU-40-M10-C-RT | 40 | 37 | 22 | M10 | 18 | 43 |
| DIN 319-KU-40-M10-E | 40 | 37 | 22 | M10 | 15 | 55 |
| DIN 319-KT-40-M12-C | 40 | 37 | 22 | M12 | 18 | 42 |
| DIN 319-KU-40-M12-C | 40 | 37 | 22 | M12 | 18 | 42 |

| | | | | | | |
|------------------------|----|----|----|-----|----|-----|
| DIN 319-KU-50-M12-C | 50 | 46 | 27 | M12 | 21 | 83 |
| DIN 319-KU-50-M12-C-RT | 50 | 46 | 27 | M12 | 21 | 83 |
| DIN 319-KU-50-M12-E | 50 | 46 | 27 | M12 | 18 | 107 |



STANDARD MACHINE ELEMENTS WORLDWIDE

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Knobs & Dials](#) category:

Click to view products by [Elesa & Ganter](#) manufacturer:

Other Similar products are found below :

[85-559](#) [8573](#) [11K5015-EMNB](#) [11K5017-JCAG](#) [1770](#) [P400S-08-D6-N](#) [KNP700A1/4](#) [3045B](#) [AL811BA18](#) [AR22PY-122B](#) [PKJ50B18](#)
[42000B38](#) [5006](#) [56008-001](#) [420037B14](#) [WA-102B](#) [WA-109B](#) [WA-1550](#) [WA-1600-P](#) [WA-2300](#) [8517](#) [WA-4104](#) [WA-4103](#) [WA-1202](#)
[WA-103B](#) [WA-102](#) [7-1437622-0](#) [8-1437622-6](#) [P209061-001](#) [P675S-06-D6-W](#) [P861H-0X-S6](#) [WA-1600A](#) [WA-1204](#) [WA-1200](#) [11K5014-](#)
[ECNG](#) [DDS-75-1-6](#) [11K5019-KCNG](#) [11K5028-KCNG](#) [VCT.40 B-M8-C3](#) [4-1437471-1](#) [85-571](#) [HP50294](#) [3010B](#) [UTC133](#)
[G813512LADUS-0](#) [2810-Y](#) [2965GQ](#) [3009CC](#) [3025BA](#) [3093](#)