

Pin-in-Paste 10/100 FastJack™

1x1 Tab-Up Pin-in-Paste 10/100BASE-T Integrated RJ45



Product Features:


- Ethernet RJ45 with Magnetics
- Compatible with SMT Reflow Process
- 30µ" Gold Plating (min) on Contacts
- 100% IEEE802.3u Compliance Testing
- 1500Vrms Hi-Pot
- Proprietary Robust Contact Design

Part Number	Operating Temp Range	Bandwidth	Circuit	PoE	LED's (L/R)	Return Loss (min)			
						0.5-30MHz	40MHz	50MHz	60-80MHz
HFJT1-PP50RL	0°C to +70°C	10/100	A	-	None	-18dB	-15.5dB	-13.6dB	-12dB
HFJT1-PPE50RL	-40°C to +85°C	10/100	A	-	None	-18dB	-15.5dB	-13.6dB	-12dB


Notes:

1. Versions with LED's available. Please contact factory.
2. Part specific datasheets available


Mechanical



Circuit A



Footprint



Recommended PC Board Pattern (Comp. Side)
*Adjust Hole Size Based on Customer Process Tolerances



2880 Lakeside Drive #116
Santa Clara, CA 95054
(650) 903-3800
www.haloelectronics.com

HALO® Electronics is a leading supplier of high quality communication magnetics including signal transformers, filters, CMR chokes, PoE power transformers, DC/DC converters, and integrated Ethernet connectors. HALO's leading edge technology solutions are manufactured in ISO9001 and ISO14001 factories offering high quality products at a competitive price.

© Copyright 2017 HALO Electronics, Inc. All rights reserved.

Revised 03/2019. Download the latest version at www.haloelectronics.com/pdf/fastjack-tabuppip-100baset.pdf

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Modular Connectors / Ethernet Connectors](#) category:

Click to view products by [HALO](#) manufacturer:

Other Similar products are found below :

[8949-H88/06BLKA/SN](#) [74441-0010/BKN](#) [MP1010RX-1000](#) [MP44RX-1000](#) [PHJ-4P4C-1-V-4](#) [PHP-6P6C-5](#) [GAX-3-66](#) [GAX-8-62](#) [GDCX-PA-66-50](#) [GDCX-PN-64](#) [GDCX-PN-66](#) [GDCX-PN-66-50](#) [GDLX-A-66](#) [GDLX-N-66](#) [GDLX-S-66](#) [GDLX-S-88K](#) [GDLX-SMT-S-88](#) [GDTX-S-88-50](#) [GDX-PA-1010](#) [GLX-N-1010M-BLK](#) [GLX-S-88M-BLK](#) [GMX-N-1010](#) [GMX-S-1010](#) [GMX-S-66](#) [GMX-SMT4-N-88](#) [GPX-2-64](#) [GSGX-N-2-88](#) [GSGX-N-4-88](#) [GSX-NS2-88-3.05](#) [GSX-NS2-88-3.05-50](#) [GSX-NS-88-3.05-50](#) [PT-108A-8C-UL](#) [PT-J951-8C](#) [PTS-J531-8CS-50UL](#) [1-1775629-2](#) [A-2014-0-4](#) [GWLX-S-88-GR](#) [GWLX-S9-88-YG](#) [DC-1021-8-WH-6](#) [1300530003](#) [1324640-4](#) [RJ11FTVC2G](#) [RJ11FTVC2N](#) [RJFTVX2SA1G](#) [132764-001](#) [1413235](#) [MP88X-1000](#) [MPS88RX-5000](#) [E5288-S000K3-L](#) [E5908-15A242-L](#)