

GNSSoF

Power supply, DC to DC, GNSS over fiber, 2 power IN, 2 power OUT

Direct GPSoF DC/DC Converter

Properties

- 18-75VDC to 12VDC converter designed to power HUBER+SUHNER GPS-over-Fiber and Direct GPS-over-Fiber.
- Allows for stable power infrastructure of up to two GPS-over Fiber products.
- 2 input ports for redundancy support



General data	
Product family	GNSSoF auxiliary tools
Suitable Products	GPSoF16-2 (RX) 85145447
	Direct GPSoF - MAC8-1 (RX) 85128283
	GPSoF Amp Expansion Module 32 85128404
Safety standard	UL62368-1 2nd edition
Electrical data	
Supply voltage range	18 V DC ... 75 V DC
Supply voltage typical	48 V DC
Input current maximal	0.8 A
Input inrush current	20 A
Efficiency	90 %
Number of input ports	2
Rated power	30 A
Ripple & noise mVp-p 60	60 mVp-p
Voltage tolerance	± 2 %
Line regulation	± 0.3 %
Load regulation	± 0.3 %
Setup rise time	120 ms, 85 ms at full load
Number of output ports	2
Mechanical data	
Weight	1.01 kg
Dimensions (LxWxH)	285mm x 430mm x 44mm
Housing material	Aluminium
Input interface	Screw terminal connector
Output interface	Cable 2m + 3 pole connector included
Cables	2 pices2m (3x 0.75mm ²)

GNSSoF
Power supply, DC to DC, GNSS over fiber, 2 power IN, 2 power OUT
Direct GPSoF DC/DC Converter

Environmental data	
Storage temperature	-40 °C ... 85 °C
Operation case temperature	-40 °C ... 55 °C
Humidity receiver in % max	5 - 95 %
Temperature coefficient	±0.03%/°C (0-50°C)

Mechanical interface		
	Input- 48 VDC IN 1 & 48 VDC IN 2	Ouput- 12 VDC OUT 1 & 12 VDC OUT 1
Interface Description	Screw terminal connector	3 Pole connector socket

Technical drawing

Front view



Back view



12VDC Power cable



Scope of delivery	
Scope of delivery	2x pieces 2m (3x 0.75mm^2) 3 pole connector assembly

Ordering Information Table	
Item number	Item description
85152769	Direct GPSoF DC/DC Converter

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [GNSS / GPS Modules](#) category:

Click to view products by [Huber & Suhner](#) manufacturer:

Other Similar products are found below :

[SA868-U](#) [SA828-U](#) [SA828-V](#) [ATGM336H-5N71](#) [ATGM336H-6N-22](#) [AT6668-6N-74](#) [ATGM331C-5N-31](#) [ATGM332D-6N22](#)
[LC29HEAEK](#) [LC29HBAEK](#) [NEO-M9V-20B](#) [AIW-210XU-001](#) [WISE-4610P-NA](#) [M10578-A2](#) [M10578-A3](#) [M20071](#) [M20072](#) [AS-PRO-](#)
[CORS-L125ETH-01](#) [AS-PRO-HANDHELD2-0](#) [AS-RTK-MICRO-X20P-SMATH](#) [AS-RTK-MICRO-X20P-UFLTH](#) [CMM21T-900M-N](#)
[DFR1103](#) [KIT0198-EU](#) [KIT0198-US](#) [KIT0212](#) [TEL0137](#) [TEL0138](#) [POL-3G](#) [D-GNSSoF1-1R-L12](#) [D-GNSSoF1-1T-L12](#) [Direct GPSoF](#)
[DC/DC Converter](#) [ISM3333-C6.1](#) [PNT-SG3FS-CT](#) [PNT-SG3FS-TR](#) [RXM-GPS-F4-T](#) [M003-V21](#) [M135](#) [U190](#) [A5135-H](#) [MIKROE-4150](#)
[28504](#) [L26-M33](#) [L26T-S89](#) [L70B-M39](#) [L76L-M33](#) [L76-M33](#) [L86-M33](#) [L89HA-S90](#) [L89-S90](#)