

# CLAMP METER FOR PV APPLICATIONS

## DCM8500PV



- TRMS measurements
- 6000 counts LCD
- 2000 V CC
- 1500 V CA
- 600 A AC/DC
- Capability for low currents measurement ( $\mu\text{A}$  CA/CC)
- Resistance, frequency, capacitance, diode test, continuity test.
- Non contact Voltage Detection
- Temperature Measurement ( $^{\circ}\text{C}/^{\circ}\text{F}$ )
- Inrush current
- High Frequency rejection function
- Auto-ranging
- Datalogging
- Bluetooth connectivity through *KPS Link* APP
- Safety rating: CAT IV 600V/CAT III 1000V



# DCM8500PV

## CLAMP METER FOR PV APPLICATIONS

General	
Display	6000 counts
Auto power off	✓
Backlight	✓
Hold	✓
High Frequency Rejection	✓
Diode and continuity test	✓
Auto-ranging	✓
MIX/MAX/AVG	✓
ZERO/REL	✓
Non Contact Voltage Detection	✓
Wireless Conectivity	✓
Datalogging	4000
Jaw size	37mm
Dimensions	62x240x41mm
Torch	✓
Weight	430g
Batteries	NEDA 15A/IEC LR6, 2*1,5V
Standars	EC 61010-1, IEC/EN61010-2-033
Safety rating	CAT IV 600V, CAT III 1000V
Accesories included	Standard test leads, PV test leads, termocouple and punch

# DCM8500PV

## CLAMP METER FOR PV APPLICATIONS

Specs	
TRMS	✓
DC Voltage (mV)	600mV
DC Voltage (V)	1000V
DC Voltage PV mode (V)	2000V
AC Voltage (V)	1000V
AC Voltage PV mode (V)	1500V
AC/DC low Current (μA)	400μA/4000μA
DC Current	600A
AC Current	600A
Flexible clamp AC current (opcional)	300A/3000A
Frequency	10kHz
Resistance	600kΩ
Diode Test	1,5V
Continuity Test	✓
Capacitance	1000μF
Temperature	-40°C - 400°C

Product Code Information	
SKU	KPSDCM8500PVCBINT
EAN code	8435394784694
UPC code	810053676608
Pcs/export carton	20

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [KPS manufacturer](#):*

Other Similar products are found below :

[KPSCC800CBINT](#) [KPS-CF100](#) [KPS-CP300](#) [KPSDCM3000CBINT](#) [KPSDCM3500TCBINT](#) [KPSDCM4000TCBINT](#)  
[KPSDCM8500PVCBINT](#) [KPSDCM8700PVCBINT](#) [KPS-DG100](#) [KPSDMM4500PV](#) [KPS-DT120](#) [KPSDT220CBINT](#) [KPS-MA100](#) [KPS-](#)  
[MT440](#) [KPS-MT460](#) [KPS-MT470](#) [KPS-MT480](#) [KPSMT490CBINT](#) [KPS-MT700](#) [KPSMT70CBINT](#) [KPS-MT720](#) [KPS-MT740](#) [KPS-](#)  
[MT920](#) [KPS-PA430MINI](#) [KPS-PA440](#) [KPSPA700CBINT](#) [KPS-PT100](#) [KPS-PT120](#) [KPS-PT15](#) [KPS-PT20](#) [KPS-PW300](#) [KPS-SL100](#) [KPS-](#)  
[SMD520](#) [KPS-TP120](#) [KPS-TP320](#)