

SB120 thru SB1100

Schottky Barrier Rectifiers
Reverse Voltage 20 to 100V Forward Current 1.0A

Feature & Dimensions

- * Plastic package has Underwriters Laboratory Flammability Classification 94V-0
- * Low power loss, high efficiency
- * For use in low voltage high frequency inverters, free wheeling, and polarity protection applications
- * Guarding for over voltage protection
- * High temperature soldering guaranteed:
260°C/10 seconds at terminals

Mechanical Data

Case: JEDEC DO-41, molded plastic over glass body


Terminals: Plated axial leads, solderable per MIL-STD-750, Method 2026

Polarity: Color band denotes cathode end

Mounting Position: Any

Weight: 0.011 oz., 0.284 g

Handling Precaution: None



We declare that the material of product compliance with ROHS requirements

1. Electrical Characteristic

Maximum Ratings & Thermal Characteristics Ratings at 25°C ambient temperature unless otherwise specified.

| Parameter Symbol | symbol | SB 120 | SB 130 | SB 140 | SB 150 | SB 160 | SB 180 | SB 190 | SB 1100 | Unit |
|--|-----------------------------------|-------------|-----------|-----------|-----------|-----------|-----------|-----------|------------|------|
| Maximum repetitive peak reverse voltage | V _{RRM} | 20 | 30 | 40 | 50 | 60 | 80 | 90 | 100 | V |
| Maximum RMS voltage | V _{RMS} | 14 | 21 | 28 | 35 | 42 | 56 | 63 | 70 | V |
| Maximum DC blocking voltage | V _{DC} | 20 | 30 | 40 | 50 | 60 | 80 | 90 | 100 | V |
| Maximum average forward rectified current 0.375" (9.5mm) lead length (See fig. 1) | I _{F(AV)} | 1.0 | | | | | | | A | |
| Peak forward surge current 8.3ms single half sine-wave superimposed on rated load (JEDEC Method) | I _{FSM} | 30 | | | | | | | A | |
| Typical thermal resistance (Note 1) | R _{θJA} | 35 | | | | | | | °C/W | |
| Operating junction and storage temperature range | T _J , T _{TSG} | -40 to +125 | | | | | | | °C | |

Electrical Characteristics Ratings at 25°C ambient temperature unless otherwise specified.

| Parameter Symbol | symbol | SB 120 | SB 130 | SB 140 | SB 150 | SB 160 | SB 180 | SB 190 | SB 1100 | Unit |
|---|----------------|-----------|-----------|-----------|-----------|-----------|-----------|-----------|------------|------|
| Maximum instantaneous forward voltage at 1.0A | V _F | 0.50 | | | 0.70 | | 0.84 | | | V |
| Maximum DC reverse current TA = 25°C at rated DC blocking voltage TA = 100°C | I _R | 0.5 | | | 10 | | | | | mA |
| Typical junction capacitance at 4.0V, 1MHz | C _J | 110 | | | | | | | PF | |

NOTES:

1. Thermal resistance from junction to ambient at 0.375" (9.5mm) lead length, P.C.B. mounted

SB120 thru SB1100

2. Characteristic Curves (TA = 25°C unless otherwise noted)

Fig. 1 – Forward Current Derating Curve




Fig. 3. – Typical Instantaneous Forward Characteristics




Fig 5. –typical transient thermal impedance




Fig. 2 – Maximum Non-repetitive Peak Forward Surge Current




Fig 4. – Typical Reverse Characteristics





Fig 6. – Typical Junction Capacitance



SB120 thru SB1100**3. dimension:**

| Package outline | | | | | |
|-----------------|------------|-------|-------|------|--|
| | Dimensions | | Note: | | |
| | inches | | mm | | DO-41 |
| L | Min. | Max. | Min. | Max. | molded plastic case |
| L1 | 0.166 | 0.205 | 4.2 | 5.2 | The marking band indicates the cathode |
| ΦD | 0.080 | 0.107 | 2.0 | 2.7 | |
| Φd | 0.028 | 0.034 | 0.7 | 0.9 | |



LESHAN RADIO COMPANY, LTD.

SB120 thru SB1100

4. Update Record

| 版次 | 更新记录 | 更新作者 | 更新日期 |
|----|------|------|-----------|
| 1 | 第一版 | 余波 | 2010-5-27 |
| | | | |
| | | | |
| | | | |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Schottky Diodes & Rectifiers category:

Click to view products by Leshan manufacturer:

Other Similar products are found below :

[MA4E2039](#) [MA4E2508M-1112](#) [MBR1545CT](#) [MMBD301M3T5G](#) [RB160M-50TR](#) [D83C](#) [BAS16E6433HTMA1](#) [BAT 54-02LRH E6327](#)
[NRVBAF360T3G](#) [NSR05F40QNXT5G](#) [NTE555](#) [JANS1N6640](#) [SK310-T](#) [SK34B-TP](#) [SS3003CH-TL-E](#) [GA01SHT18](#)
[CRS10I30A\(TE85L,QM](#) [MA4E2501L-1290](#) [MBRA140TRPBF](#) [MBRB30H30CT-1G](#) [BAT 15-04R E6152](#) [JANTX1N5712-1](#) [DMJ3940-000](#)
[SB007-03C-TB-E](#) [SK33B-TP](#) [NRVBB20100CTT4G](#) [NRVBM120LT1G](#) [NTSB30U100CT-1G](#) [VS-6CWQ10FNHM3](#) [CRG04\(T5L,TEMQ\)](#)
[ACDBA1100LR-HF](#) [ACDBA1200-HF](#) [ACDBA240-HF](#) [ACDBA3100-HF](#) [CDBQC0530L-HF](#) [CDBQC0240LR-HF](#) [ACDBA260LR-HF](#)
[ACDBA1100-HF](#) [MA4E2502L-1246](#) [10BQ015-M3/5BT](#) [NRVBM120ET1G](#) [CRS08TE85LQM](#) [PMAD1108-LF](#) [B120Q-13-F](#) [1N5819T-G](#)
[B0530WSQ-7-F](#) [PDS1040Q-13](#) [B160BQ-13-F](#) [SDM05U20CSP-7](#) [B140S1F-7](#)