Opti-Core® Push-Pull LC Duplex Fiber Optic Patch Cords



technical information

Push-Pull LC Duplex Fiber Optic Patch Cords containing the custom push-pull strain relief boot and duplex clip, allow users easy accessibility when deploying very high density LC patch fields in data center applications. Available in riser (OFNR), and low smoke zero halogen (LSZH) rated jacket materials to comply with local cabling ordinances and OM4, OM3 or OS1/OS2 fiber types to meet the demands of today's highest speed applications.



application

Provide interconnect and cross-connect of applications in entrance facilities, telecommunication rooms, data centers, at the desk and network applications to interconnect pre-terminated cassettes in main distribution, horizontal distribution, and equipment distribution areas.

construction

Fiber count:	Duplex (2-fiber) jacketed zipcord	
Cable jacket ratings:	Riser (OFNR) Low Smoke Zero Halogen (LSZH) per: IEC 60332-1-2, IEC 60332-3-24, IEC 60754-1, IEC 60754-2, IEC 61034-2	
Fiber types:	Singlemode: OS1/OS2 9/125µm Multimode: OM3 50/125µm OM4 50/125µm	
Connector types, End 'A':	Duplex LC	
Connector types, End 'B':	Duplex LC	
Jacket color:	OS1/OS2: Yellow OM3: Aqua OM4: Aqua	

physical properties

Cable outside diameter (OD):	1.6mm duplex
Bend Radius (min) Short-Term:	16mm
Bend Radius (min) Long-Term:	32mm
Connector cable retention:	50N (4.24lb) @ 0° 19.4N (4.4lb)@ 90°
Connector durability:	500 cycles

optical properties

Connector insertion loss:	Optimized:	0.25dB max (OM3 and OM4) 0.35dB max (OS2) 0.15dB max (OM3 and OM4) 0.10dB max (OM4)
Connector return loss:	26dB min (OM3 and OM4) 55dB min (OS1/OS2)	

environmental properties

Storage and wshipping temperature:	-40°C to 70°C
Operating and installation temperature:	-10°C to 60°C

standards

Meets or exceeds ISO/IEC 11801, TIA-568-C.3, TIA-604-10 (FOCIS-10)

Restriction of Hazardous Substances (RoHS) Compliance:

All patch cord components meet the requirement of Directive 2002/95/EC

Opti-Core® Push-Pull LC Duplex Fiber Optic Patch Cords

5

R

part number configurator

Example: FX2ERQ1Q1SNM005 = Fiber, OM3, 2-fiber, 1.6mm cable, riser rated, LC push-pull connector to LC push-pull connector, standard IL, 5 meters

Character

Example

1 2 F X

2

4 E 6 Q 7

8 Q 10 S

9

1

11 N

12 13 M 0

14

15 5

1 - Fiber Product

F = Fiber

2 - Fiber Type

 $X = OM3 50/125 \mu m$

 $Z = OM4 \ 50/125 \mu m$

 $9 = OS1/OS2 9/125 \mu m$

3 - Fiber Count

2 = 2-fiber

4 - Cable Type

E = 1.6mm

5 - Jacket Type

L = LSZH (Low Smoke Zero Halogen)

R = OFNR (Riser)

6 - Connector Type

Q = LC Push-Pull connector

7 - Connector Variant

1 = 1st Gen (Low Profile Duplex LC)

8 - Connector Type

Q = LC Push-Pull connector

9 - Connector Variant

1 = 1st Gen (Low Profile Duplex LC)

10 - Performance/Construction

S = Standard IL/Straight Through

O = Optimized IL/Straight Through

N = Ultra IL/Straight Through (A-B)

11 - Connector Variant

N = No variant

12 - Unit of Length


M = Meters


F = Feet

13, 14, 15 - Length


001 - 050 in 1 meter increments 1/2 meter increments available between 1 and 10 meters, ex 3.5 Foot-length increments available from 1 to 25 feet in Riser-rated jacket only

polarity changeover





Carefully slide boot backward while still squeezing sides.



Remove both connectors from duplex clip and switch positions of A/B. Only perform this change on one end of the patch cord.

Other options are available as follows; contact Panduit for part number.

Fiber type: OM4+ Signature Core

Performance/Construction: Optimized IL - Straight Through (A-B), Optimized IL - Flipped (A-A),

Standard IL - Flipped (A-A)

WORLDWIDE SUBSIDIARIES AND SALES OFFICES

PANDUIT CANADA Markham, Ontario cs-cdn@panduit.com Phone: 800.777.3300 PANDUIT EUROPE LTD. London, UK cs-emea@panduit.com Phone: 44.20.8601.7200 PANDUIT SINGAPORE PTE. LTD. Republic of Singapore cs-ap@panduit.com Phone: 65.6305.7575

PANDUIT JAPAN Tokyo, Japan cs-japan@panduit.com Phone: 81.3.6863.6000 PANDUIT LATIN AMERICA Guadalajara, Mexico cs-la@panduit.com Phone: 52.33.3777.6000 PANDUIT AUSTRALIA PTY. LTD. Victoria, Australia cs-aus@panduit.com Phone: 61.3.9794.9020

For a copy of Panduit product warranties, log on to www.panduit.com/warranty

For more information

Visit us at www.panduit.com

©2015 Panduit Corp. ALL RIGHTS RESERVED. FBSP90--WW-ENG 2/2015



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Wire Ducting & Raceways category:

Click to view products by Panduit manufacturer:

Other Similar products are found below:

```
800A-LB 801I-LSP 802A-ECSP 802I-ICSP 923223-000 PRAF6WH-X A0405538 1301150342 1301160034 1301170070 1301180011 1301230083 1301230153 1301240273 1301250006 1302261238 1302261321 1302262552 1302263103 1302263178 1302263259 1302263816 1302263860 1302264375 1302264390 1301150343 1301160030 1301170050 1301170051 1301170061 1301180013 1301230086 1301230130 1301240054 1302260055 1302260376 1302261343 1302261344 1302262674 1302263095 1302263166 1302263209 1302263513 1302263851 1302263870 1302264137 1302264218 DD1/J AX101472 AX102007
```