



LOGO! 24CEo, logic module, without display, power supply / I/O: 24 V/24 V/24 V trans., 8 DI (4 AI)/4 DO, memory 800 blocks, modularly expandable, Ethernet, integrated web server, data log, user-defined web pages, standard microSD card for LOGO! Soft Comfort V9.0 or higher, older projects executable, cloud connection, MQTT in all LOGO! basic units

Display	
with display	No
Installation type/mounting	
Mounting	on 35 mm DIN rail, 4 spacing units wide
Supply voltage	
Rated value (DC)	
• 24 V DC	Yes
permissible range, lower limit (DC)	20.4 V
permissible range, upper limit (DC)	28.8 V
Time of day	
Time switching clocks	
• Number	800; max. 800, function-specific
• Power reserve	480 h
Digital inputs	
Number of digital inputs	8; Of which 4 can be used in analog mode (0 to 10 V)
Digital outputs	
Number of digital outputs	4; Transistor
Short-circuit protection	Yes; electrical (1 A)
Output current	
• for signal "1" permissible range for 0 to 55 °C, max.	0.3 A
EMC	
Emission of radio interference acc. to EN 55 011	
• Limit class B, for use in residential areas	Yes; Radio interference suppression according to EN55011, Limit Value Class B
Standards, approvals, certificates	
Siemens Eco Profile (SEP)	Siemens EcoTech
CE mark	Yes
CSA approval	Yes; covered by UL cert
UL approval	Yes
FM approval	Yes
developed in accordance with IEC 61131	Yes
according to VDE 0631	Yes
Marine approval	Yes; in preparation
Ecological footprint	
• environmental product declaration	Yes
Global warming potential	

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [PLC Controllers](#) category:

Click to view products by [Siemens](#) manufacturer:

Other Similar products are found below :

[SL-TBP4-PN](#) [FP0-CCLS](#) [FP2-Y32T](#) [SL-TB4-PN](#) [CP1H-Y20DT-D](#) [EASY-E4-AC-12RCX1P](#) [EASY-E4-AC-16RE1P](#) [EASY-E4-AC-8RE1P](#)
[EASY-E4-DC-12TC1P](#) [EASY-E4-DC-16TE1P](#) [EASY-E4-DC-4PE1P](#) [EASY-E4-DC-6AE1P](#) [EASY-E4-DC-8TE1P](#) [EASY-E4-UC-12RCX1P](#)
[EASY-E4-UC-16RE1P](#) [EASY-E4-UC-8RE1P](#) [EASY-BOX-E4-AC1](#) [6GK1901-1BB30-0AA0](#) [6ES7521-1BL10-0AA0](#) [6ES7226-6RA32-0XB0](#)
[6ES7590-1AE80-0AA0](#) [TM200C32R](#) [6ES7954-8LF04-0AA0](#) [6ES7590-1AC40-0AA0](#) [XW2K40GO32C](#) [56501](#) [6AG40210AA200AA6](#)
[56527](#) [57105](#) [56521](#) [6ES75152FM020AB0](#) [6ES75262BF000AB0](#) [6AG40210AA200AA1](#) [6ES72141AF500XB0](#) [6ES72141AH500XB0](#)
[6AG12211BH322XB0](#) [6ES71314BF000AA0](#) [6ES71314BD010AA0](#) [6ES71513BA230AB0](#) [6AG11316BF007CA0](#) [6AG12315PD324XB0](#)
[6ES71384FA050AB0](#) [6ES72121HG500XB0](#) [6ES72141HH500XB0](#) [6ES73231BH010AA0](#) [6ES75111AL030AB0](#) [6ES75111FL030AB0](#)
[6ES75121DK010AB0](#) [6ES75121SM030AB0](#) [6ES75131AM030AB0](#)