

### PNP MEDIUM POWER TRANSISTOR

#### **General features**


- SURFACE-MOUNTING DEVICES IN MEDIUM POWER SOT-223 AND SOT-89 **PACKAGES**
- AVAILABLE IN TAPE & REEL PACKING

## **Description**


The STF817A - STN817A are PNP transistor manufactured using Planar Technology resulting in rugged high performance devices.

## **Applications**

- VOLTAGE REGULATION
- RELAY DRIVER
- te Productie ■ GENERIC SWITCH



### Internal schematic diagram



#### Order codes

| Sales Type | Sales Type Marking |         | Packaging   |  |
|------------|--------------------|---------|-------------|--|
| STF817A    | 817A               | SOT-89  | TAPE & REEL |  |
| STN817A    | N817A              | SOT-223 | TAPE & REEL |  |

1 Electrical ratings STF817A - STN817A

# 1 Electrical ratings

Table 1. Absolute maximum ratings

| Symbol                             | Parameter  | Va          | Unit       |   |  |
|------------------------------------|--|-------------|------------|---|--|
|                                    |  | SOT-223     | SOT-89     |   |  |
| V <sub>CBO</sub>                   | Collector-Base Voltage (I <sub>E</sub> =0)         | -{          | -80        |   |  |
| V <sub>CEO</sub>                   | Collector-Emitter Voltage (I <sub>E</sub> =0)      | -{          | -80        |   |  |
| V <sub>EBO</sub>                   | Emitter-Base Voltage (I <sub>C</sub> =0)           | -           | -5         |   |  |
| I <sub>C</sub>                     | Collector Current                                  | -1          | -1.5       |   |  |
| I <sub>CM</sub>                    | Collector Peaak Current (tp<5ms)                   | -           | -2         |   |  |
| Ι <sub>Β</sub>                     | Base Current                                       | urrent -0.3 |            | Α |  |
| I <sub>BM</sub>                    | Base Peak Current (tp<5ms)                         | -0          | -0.6       |   |  |
| P <sub>TOT</sub>                   | Total Dissipation at T <sub>amb</sub> = 25°C       | 1.6         | 1.4        | W |  |
| T <sub>j</sub><br>T <sub>stg</sub> | Operating Junction Temperature Storage Temperature | -65 t       | -65 to 150 |   |  |

Table 2. Thermal data

|                           | \ /                                 | SOT-223 | SOT-89 | Unit |
|---------------------------|-------------------------------------|---------|--------|------|
| Rthj-amb<br><i>Note</i> 1 | Thermal Resistance Junction-amb Max | 78      | 89     | °C/W |
| 0/050/8                   | te Produc                           |         |        |      |

STF817A - STN817A 2 Electrical characteristics

# 2 Electrical characteristics

(T<sub>CASE</sub> = 25 °C unless otherwise specified)

Table 3. On/off states

| Symbol                          | Parameter  | Test Conditions   | Min.            | Тур. | Max.          | Unit   |
|---------------------------------|--|---|-----------------|------|---------------|--------|
| I <sub>ECS</sub>                | Collector Cut-off Current (V <sub>BE</sub> =0)               | V <sub>CE</sub> = -80 V   |                 |      | -500          | μА     |
| I <sub>CEO</sub>                | Collector Cut-off Current (I <sub>B</sub> =0)                | V <sub>CE</sub> = -80 V   |                 |      | -1            | mA     |
| I <sub>EBO</sub>                | Emitter Cut-off Current (I <sub>C</sub> = 0)                 | V <sub>EB</sub> = -5V   |                 |      | -100          | рΑ     |
| V <sub>CEO(sus)</sub><br>Note 2 | Collector-Emitter Sustaining<br>Voltage (I <sub>B</sub> = 0) | I <sub>C</sub> =-10mA   | -80             | 9    | 70,           | V      |
| V <sub>CE(sat)</sub><br>Note 2  | Collector-Emitter Saturation<br>Volatge                      | I <sub>C</sub> = -100 mA, I <sub>B</sub> = -10m A<br>I <sub>C</sub> = -1 A, I <sub>B</sub> = -100m A    | P               |      | -0.25<br>-0.5 | V<br>V |
| V <sub>BE(sat)</sub><br>Note 2  | Base-Emitter Saturation<br>Volatge                           | I <sub>C</sub> = -100 mA, I <sub>B</sub> = -10m A<br>I <sub>C</sub> = -1 A, I <sub>B</sub> = -100m A    |                 |      | -1<br>-1.1    | V<br>V |
| h <sub>FE</sub> Note 2          | DC Current Gain  | $I_{C}$ = -100 mA, $V_{CE}$ = -2V<br>$I_{C}$ = -500 mA, $V_{CE}$ = -2V<br>$I_{C}$ = -1A, $V_{CE}$ = -2V | 140<br>80<br>30 |      |               |        |
| f <sub>T</sub>                  | Transition Frequency   | $I_C$ = -0.1A, $V_{CE}$ = -10V  |                 | 50   |               | MHz    |

<sup>(1)</sup> Device mounted on a PCB area of 1 cm<sup>2</sup>

Obsolete

**5**//

<sup>(2)</sup> Pulsed: Pulse duartion = 300µs, duty cycle 1.5%


## 3 Package mechanical data

In order to meet environmental requirements, ST offers these devices in ECOPACK® packages. These packages have a Lead-free second level interconnect . The category of second level interconnect is marked on the package and on the inner box label, in compliance with JEDEC Standard JESD97. The maximum ratings related to soldering conditions are also marked on the inner box label. ECOPACK is an ST trademark. ECOPACK specifications are available at: <a href="https://www.st.com">www.st.com</a>

Obsolete Product(s).


#### **SOT-223 MECHANICAL DATA**

| DIM | DIM. mm |      |      | inch  |       |       |  |
|-----|---------|------|------|-------|-------|-------|--|
| 2   | MIN.    | TYP. | MAX. | MIN.  | TYP.  | MAX.  |  |
| А   |         |      | 1.80 |       |       | 0.071 |  |
| В   | 0.60    | 0.70 | 0.80 | 0.024 | 0.027 | 0.031 |  |
| B1  | 2.90    | 3.00 | 3.10 | 0.114 | 0.118 | 0.122 |  |
| С   | 0.24    | 0.26 | 0.32 | 0.009 | 0.010 | 0.013 |  |
| D   | 6.30    | 6.50 | 6.70 | 0.248 | 0.256 | 0.264 |  |
| е   |         | 2.30 |      |       | 0.090 |       |  |
| e1  |         | 4.60 |      | 32    | 0.181 |       |  |
| E   | 3.30    | 3.50 | 3.70 | 0.130 | 0.138 | 0.146 |  |
| Н   | 6.70    | 7.00 | 7.30 | 0.264 | 0.276 | 0.287 |  |
| V   |         |      | 10°  |       |       | 10°   |  |
| A1  |         | 0.02 |      |       |       |       |  |



#### **SOT-89 MECHANICAL DATA**

| DIM.  | DIM mm |      | mils |       |      |       |
|-------|--------|------|------|-------|------|-------|
| DIWI. | MIN.   | TYP. | MAX. | MIN.  | TYP. | MAX.  |
| Α     | 1.4    |      | 1.6  | 55.1  |      | 63.0  |
| В     | 0.44   |      | 0.56 | 17.3  |      | 22.0  |
| B1    | 0.36   |      | 0.48 | 14.2  |      | 18.9  |
| С     | 0.35   |      | 0.44 | 13.8  |      | 17.3  |
| C1    | 0.35   |      | 0.44 | 13.8  |      | 17.3  |
| D     | 4.4    |      | 4.6  | 173.2 |      | 181.1 |
| D1    | 1.62   |      | 1.83 | 63.8  | 01   | 72.0  |
| E     | 2.29   |      | 2.6  | 90.2  |      | 102.4 |
| е     | 1.42   |      | 1.57 | 55.9  | O    | 61.8  |
| e1    | 2.92   |      | 3.07 | 115.0 |      | 120.9 |
| Н     | 3.94   |      | 4.25 | 155.1 |      | 167.3 |
| L     | 0.89   |      | 1.2  | 35.0  |      | 47.2  |



STF817A - STN817A 4 Revision History

# 4 Revision History

| Date        | Revision | Changes       |
|-------------|----------|---------------|
| 03-Nov-2005 | 1        | First release |

Obsolete Product(s). Obsolete Product(s)

**5**//

4 Revision History STF817A - STN817A

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in file support devices or systems without express writen approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners

© 2005 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

5//

STF817A - STN817A 4 Revision History

Obsolete Product(s). Obsolete Product(s)

**577** 

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Bipolar Transistors - BJT category:

Click to view products by STMicroelectronics manufacturer:

Other Similar products are found below:

619691C MCH4017-TL-H BC546/116 BC556/FSC BC557/116 BSW67A HN7G01FU-A(T5L,F,T NJVMJD148T4G

NSVMMBT6520LT1G NTE187A NTE195A NTE2302 NTE2330 NTE2353 NTE316 NTE65 C4460 SBC846BLT3G 2SA1419T
TD-H 2SA1721-O(TE85L,F) 2SA1727TLP 2SA2126-E 2SB1202T-TL-E 2SB1204S-TL-E 2SC5488A-TL-H 2SD2150T100R SP000011176

FMC5AT148 2N2369ADCSM 2SB1202S-TL-E 2SC2412KT146S 2SC4618TLN 2SC5490A-TL-H 2SD1816S-TL-E 2SD1816T-TL-E

CMXT2207 TR CPH6501-TL-E MCH4021-TL-E TTC012(Q) BULD128DT4 DDTC114EUAQ-7-F NJL0281DG NSS20500UW3TBG

732314D CMXT3906 TR CPH3121-TL-E CPH6021-TL-H SZT1010T1G 873787E